
 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 1 OF 107	

Table of Contents

1.0	Introduction.....	2
2.0	Conventions	2
3.0	Requirements	2
4.0	Network Security Issues	2
5.0	Other Warnings and Recommendations	2
6.0	General Usage.....	2
6.1	Commands.....	3
6.2	Responses.....	5
7.0	Field Properties	5
8.0	Examples.....	8
9.0	Local/Remote Control.....	9
10.0	Custom Formats.....	9
10.1	Format symbols	9
10.2	Format templates	9
11.0	Field Descriptions	11

ECCN 5E991. EXPORT CONTROL WARNING – Do not disclose or provide this document or item (including its contents) to non-U.S. Citizens or non-U.S. Permanent Residents, or transmit this document or item (including its contents) outside the U.S. without the written permission of Freedom Communication Technologies and required U.S. Government export approvals.

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 2 OF 107	

1.0 Introduction

This purpose of this document is to provide definition for the protocol interface used to command and interact with an R8000 Series Communications System Analyzer. The field description section of this document is subject to change and may vary between system versions.

2.0 Conventions

The following conventions are used herein:

Command strings are **bold** text

Response strings are ***bold italicized green*** text.

3.0 Requirements

The monitor and control (M&C) connection requires a cross-over Ethernet cable connected over a direct local network via TCP port **4000**. The interface is not currently available over a routed connection.

4.0 Network Security Issues

In order to enable the use of the monitor and control protocol, the R8000 must have its network settings configured. **The user should be aware that external security measures are required to protect the R8000 from unauthorized access.**

5.0 Other Warnings and Recommendations


While there are access restrictions when using this protocol to monitor and control the R8000, it is highly recommended that programmers be cautious and aware that this equipment is capable of generating and receiving high power signals through its configuration. **The protocol does not protect the user from improper physical connections or signal routing.** It is also recommended that programmers use the equipment ID command (*IDN?) to identify the equipment being controlled upon the initiation of a connection or following local control of the equipment.

6.0 General Usage

The M&C consists of a set of proprietary commands as well as supporting the IEEE standard equipment ID query. These various commands are used to access the menus and fields that control and report R8000 operation. Commands take the form of:

CMD[Tag[=data]]

If applicable, the Tag consists of the required region, also called the owner, of the field along with a specifier. Some fields require that the region is active in order to query or control the data. The specifier identifies the specific field or code being queried or controlled. The region and specifier are joined together with a colon ":"; e.g. DISPLAY:Span. The data is only used with write access controls and must be in the appropriate format per the field definition. The square

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 3 OF 107	

brackets ([]) illustrate these options and are not part of the actual command to be sent. All commands must be terminated by a carriage-return (CR) and line-feed (LF) character.

6.1 Commands

1. **NOOP**: This command has no affect on the R8000 but provides a mechanism for a prompt query. Programmers may use this command to poll for response of code **2** (Busy) to determine if a previous new command may still be being applied; see the field description section, Typical Completion Time.

Usage : **NOOP**

2. **GET**: Use this command to retrieve monitored information or current control settings

Usage: **GET <Tag>**

3. **SET**: Use this command to set a control to a new value

Usage: **SET <Tag>=<value>**

NOTE: If a field of Data Type BOOLEAN has no List Values then value is **F** or **T**.

4. **DO**: Use this command to have the R8000 perform a function.

Usage: **DO <Tag>**

5. **GO**: Use this command to navigate the R8000 menu tree. Some fields are only accessible if the field's required menu is active. In order to monitor or control these fields, use the **GO** command to navigate to the menu first.


Usage: **GO <Tag>**

6. ***IDN?**: Equipment ID command. Use this command to return the following formatted response:

Usage: ***IDN?**

*Freedom Communication Technologies, Inc. Communications System Analyzer
 Model:<model number>, S/N:<serial number>, System Version:<version>*

7. **ERR?** and **CLEAR**: Use these commands together to manage the error notification system of the R8000. **ERR?** queries the R8000 for error information and **CLEAR** is used to acknowledge error messages and popups. There are two usages based on the response to **ERR?**.

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 4 OF 107	

Usage : **ERR?**

Usage 1(Popup): **CLEAR <Tag>[Response]**

If a popup is active, **ERR?** will return with the popup tag, a list of valid responses, and the text message of the popup. For example:

ERR?

*0:SYSTEM:6045[POP_CONTINUE,POP_CANCEL] WARNING!
Access to USB device Press Continue to save screen capture to device
Or Press Cancel to abort*

CLEAR SYSTEM:6045[POP_CONTINUE]

0:

Usage 2(Messages): **CLEAR**

If no popup is active, the **ERR?** will respond with the number of active messages and a list of the message codes. For example:

ERR?

0:2[6040,7001]

CLEAR

0:

ERR?

0:0[]

- HELP:** Use this command to obtain limited help information. This command can return help for a command, a specific field, or a brief explanation of a prompt or message code.

Usage 1(Command help): **HELP <Command>**

Usage 2(Field help): **HELP <Tag>**

The field help is formatted to allow users to format the response into a readable body. It contains the pipe-bar character “|” at each location where a carriage return/line feed (CRLF) should be placed. For example,


HELP SYSTEM:RF

will respond with the following string:

0:Name:RF Zone|Tag:SYSTEM:RF|Commands:GO|Data Type:SUBMENU|Typical Completion Time:250 ms|

By replacing all pipe-bar characters with a CRLF, the result is this:

0:Name:RF Zone

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 5 OF 107	

Tag:SYSTEM:RF
Commands:GO
Data Type:SUBMENU
Typical Completion Time:250 ms

Usage 3(Prompt\Message code): **HELP <code>**

6.2 Responses

Each command sent to the R8000 via the M&C protocol shall return a single response. The response consists of a prompt code and colon followed by any returned data. The returned data format depends on the field's data type.

1. Prompt codes
 - a. **0**: Okay – command was successful
 - b. **1**: Ranged – command was accepted but the data had to be coerced into the valid data range or format.
 - c. **2**: Busy – command was accepted (i.e. code would have been Okay) but previous command was not confirmed complete based on Typical Completion Time.
 - d. **3**: Denied – Access to the requested field was denied. Check field Commands property.
 - e. **4**: N/A – Not available at this time. Check availability requirements.
 - f. **5**: Option – Option not installed. Contact Sales to purchase options.
 - g. **6**: Error – Unexpected error.
 - h. **7**: Invalid – Command not valid for field. Check field Commands property.
 - i. **8**: Unknown – Tag is unknown. Check Region and Tag
 - j. **9**: Format – Data is in the wrong format. For example, the field is an INTEGER type but a character string was sent. Check field data type.


7.0 Field Properties

Fields are described by their set of properties. This section describes the field properties, valid commands for them, type of data, availability conditions, typical command completion times, etc.

1. Name: This is the name of the field. It is unused in the protocol but valuable for reference as this name corresponds to the name found on soft keys for controls on the R8000. It is also may be slightly more descriptive than the tag.
2. Tag: The tag consists of two parts; the Region, or owner, categorizes the scope of the tag reference; the tag itself specifies the particular field within the region.

The format of the Tag is always Region:Tag

3. Commands: this property is a list of valid M&C commands that may be used with the field.

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 6 OF 107	

4. Data Type: This describes the type of data expected in the **SET** command string or the data returned from a **GET** query. All data is passed in text string format, however the string is processed by the R8000 according to the data type.
 - a. Format: Some STRING and Numeric data fields have a specialized format for the data. See 10.0 Custom Formats.
 - b. Char set: Some STRING data fields are restricted to the character set that can be used. For example, the DTMF Code has a defined character set:

0,1,2,3,4,5,6,7,8,9,A,B,C,D,#,*
 - c. List Values: Both LIST and BOOLEAN data type fields have aliased text strings to make the command/response more readable. These aliases correspond to the horizontal soft key position or position in the list box in the R8000 editing system.

Some LIST and BOOLEAN data type values are dynamically available based on the condition of the system at the time of the command. These conditions are documented in brackets immediately following the list value and describe the run-time conditions necessary to set the field to the specific list value. For example, the following field description indicates availability conditions for both list values:


Name:Select Audio Measurement
 Tag:METER:Audio Meter
 Commands:GET, SET
 Data Type:LIST
 List Values: SINAD/Ext Distortion [Test Mode<>P25 Trunk and Test Mode<>NXDN Trunk], Internal Distortion [Test Mode=Standard]
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=SINAD/Distortion
 Typical Completion Time:100 ms

The **SINAD/Ext Distortion** value is available in all test modes except trunking modes.

The **Internal Distortion** is only available in Standard test mode.

NOTE: Do not include the condition when setting a value; the correct command for this example is: SET METER:Audio Meter=SINAD/Ext Distortion

- d. Range: Numeric values may have limited ranges that will be accepted. If the number has settable units (See Units), the range is always defined in the base units. If the data set into the field is outside the range, the R8000 will coerce the

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 7 OF 107	

new value into the range at either the minimum or maximum value. The command will be accepted and return with a prompt code of **I** (Ranged)

- e. Units: Some floating point values have settable units that the value can be set in. If the field has settable units, this property will list the valid entries. To set a floating point value with its units, format the data as “value units”; for example:

SET RF:Monitor Frequency=1.2 GHz
0:1.20000000 GHz


However, sending the units is not a requirement. If units are not sent, the system will apply the currently configured units to the data. For example, if the following two commands are sent, the second will be assumed to be in MHz.

SET RF:Monitor Frequency=403 MHz
0:403.000000 MHz
SET RF:Monitor Frequency=405
0:405.000000 MHz

5. Availability

Because the R8000 disables sub-systems to provide the most efficient use of processing, certain fields may not be available at all times. Fields that have availability requirements are denoted under this property.

- a. Synth Format: Field is only accessible when the specified Audio Format is selected. This availability requirement is unique to fields in the Audio Zone and used to configure specific audio formats such as PL, DPL, etc.
 - b. Operating Mode: Field is only accessible when the R8000 is in the mode(s) indicated. If this property is not present, the field is available in any/all modes unless otherwise unavailable.
 - c. Options: Field is only accessible when the specified option has been purchased. If this property is not present, the field is standard. Contact to purchase new options for your R8000.
 - d. Menu: Field is only accessible when the R8000 menu system has the given condition active. This condition may specify a region or a region and a subzone (Region ->Subzone). Use the **GO** and **SET** commands to navigate to and/or select the appropriate region. If this property is not present, the field is available regardless of region.
6. Typical Completion Time: This property provides the typical processing time for the field in milliseconds. Most commands take very little time to complete; however some commands take more time to apply the desired condition to the system. This is particularly important when creating automated control software. The M&C is designed for immediate command response. However if the previous command has not had time to complete, there is no guarantee that data will be ready to retrieve following a change in

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 8 OF 107	

configuration. For example, the following commands if sent without delay would most likely result in an inaccurate Input Level reading:

```

SET RF:Monitor Frequency=403 MHz
0:403.000000 MHz
GET MONITOR:Input Level
2:-32.3

```

The prompt will be returned with code **2** (Busy) if the previous command was not given enough time to complete its transaction.

8.0 Examples

There are a few examples of how to use different types of commands with fields within the following section. These examples assume the R8000 is starting from the main zone screen and call specific commands to activate the required regions necessary to command the field. These examples are given as if executed from a terminal with a connection to the remote monitor and control interface. Expected command responses are provided for reference.


1. Tune to local radio station with the highest signal. From a terminal program execute the following commands in sequence.

```

SET SYSTEM:Mode Request=Monitor
0:Monitor
GO SYSTEM:RF
0:
SET RF:Monitor Port=Antenna
0:Antenna
SET RF:Bandwidth=200 kHz (Wide)
0: 200 kHz (Wide)
GO SYSTEM:DISPLAY
0:
SET DISPLAY:Subzone=Spec An
0:Spec An
SET DISPLAY:Start Frequency=75 MHz
0:75.000000 MHz
SET DISPLAY:Stop Frequency=110 MHz
0:110.000000 MHz
DO DISPLAY:Center Peak
0:
SET DISPLAY:Span=158 kHz
0:158.000 kHz

```

2. Generate a DTMF tone and view it on the modulation scope. From a terminal program execute the following commands in sequence.

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 9 OF 107	

SET SYSTEM:Mode Request=Generate

0:Generate

GO SYSTEM:DISPLAY

0:

SET DISPLAY:Subzone=Mod Scope

0:Mod Scope

SET DISPLAY:FM Vertical Scale=5 kHz

0:5 kHz

GO SYSTEM:AUDIO

0:

SET AUDIO:Gen DTMF=12

0:12

SET AUDIO:DTMF Code=123ABC#

0:123ABC#-----

SET AUDIO:DTMF Mode=Continuous

0:Continuous

9.0 Local/Remote Control

The R8000 will temporarily lock out local users when the unit is remotely controlled. When the R8000 is in lock-out, the Operating Mode indicator on the lower-left part of the screen will flash between the operating mode and "Remote". To regain local control the Esc key must be pressed from the front panel.

10.0 Custom Formats

Some fields use a custom formatting that is required for data entry. This section describes each format type.

10.1 Format symbols


- \$ Alphabetic characters only (A-Z)
- # Decimal digits only (0-9)
- 0 Hexadecimal characters only (0-9, A-F)
- x Any/all characters are valid
- : Location in string must be a colon
- . Location in string must be a period.

10.2 Format templates

0x0000 – Hexadecimal format. This field is a string containing a hexadecimal value the length of the number of digits to the right of the 0x prefix. If the data is shorter than the format, add leading zeros to ensure the appropriate value is set.

Examples:

Format=0x0000

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 10 OF 107	

Setting => 0A3F

Format=0x00

Setting => 3F

Format=0x00000000

Setting => 00000A3F

#.##### – Floating point format. This field contains a floating point number with the precision defined by the number of digits to the right of the decimal point.

Examples:

Format=#.##

Setting => 4.02

Format=#.#####

Setting => 1.10031

(POCSAGCustom) – Used for blank formatting and the POCSAG text messaging, no particular formatting required.

(56Tone) - Used specifically for the 5/6 Tone code formatting. The 5/6 tone must be formatted as #-#####c where c is either empty or 'X' indicating the 6-tone. The valid character set for the digital format (#) is [0123456789R] where the 'R' character indicates a repeat tone.

Examples:

0-12345

2-12R45


0-12346X

(DTMFCode) – Used specifically for the DTMF Tone code formatting. The DTMF code field must be at exactly 16 characters long. Strings less than 16 characters will be appended with dashes "-" to extend the string to 16 characters. Strings longer than 16 characters will be truncated to 16 characters. The valid character set for DTMF code is [0123456789ABCD#*]

(GENSEQCode) - Used specifically for the General Sequence tone code, delay, and duration sequence formatting. These fields must be at exactly 20 characters long. Strings less than 20 characters will be appended with dashes "-" to extend the string to 20 characters. Strings longer than 20 characters will be truncated to 20 characters. The valid character set for the General Sequence format is [0123456789ABCDEFGHIJ]

(HH:MM) – Used for time entry where HH is 24-hour notation; MM is minutes. This field must have a colon in the 3rd character position.

(MM.DD.YYYY) – Used for date entry where MM is month, DD is day, and YYYY is year. This field must have a period in the 3rd and 6th character positions.

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 11 OF 107	

11.0 Field Descriptions

This section provides the specific properties for each field accessible through the R8000 Monitor and Control interface for R8000 system version 3.4.2.0.

Name:RF Zone
 Tag:SYSTEM:RF
 Commands:GO
 Data Type:SUBMENU
 Typical Completion Time:1000 ms

Name:AUDIO Zone
 Tag:SYSTEM:AUDIO
 Commands:GO
 Data Type:SUBMENU
 Typical Completion Time:1000 ms


Name:DMR
 Tag:SYSTEM:DMR
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Option:R8-DMR
 Typical Completion Time:2000 ms

Name:PROJECT 25
 Tag:SYSTEM:P25
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Option:R8-P25
 Typical Completion Time:2000 ms

Name:P25 II
 Tag:SYSTEM:P25_II
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Option:R8-P25_II
 Typical Completion Time:2000 ms

Name:NXDN™
 Tag:SYSTEM:NXDN
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Option:R8-NXDN
 Typical Completion Time:2000 ms

Name:dPMR
 Tag:SYSTEM:DPMR
 Commands:GO
 Data Type:SUBMENU
 Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 12 OF 107	

Option:R8-DPMR
 Typical Completion Time:2000 ms

Name:P25 Trunk
 Tag:SYSTEM:P25_TRUNK
 Commands:GO
 Data Type:SUBMENU
 Availability:

Option:R8-P25TRNK
 Typical Completion Time:2000 ms

Name:PTC-ACSES
 Tag:SYSTEM:PTC_ACSES
 Commands:GO
 Data Type:SUBMENU
 Availability:

Option:R8-PTC_ACSES
 Typical Completion Time:2000 ms

Name:PTC-ITCR
 Tag:SYSTEM:PTC_ITCR
 Commands:GO
 Data Type:SUBMENU
 Availability:

Option:R8-PTC_ITCR
 Typical Completion Time:2000 ms

Name:TETRA
 Tag:SYSTEM:TETRA
 Commands:GO
 Data Type:SUBMENU
 Availability:

Option:R8-TETRA_BSM, R8-TETRA_DMO
 Typical Completion Time:2000 ms


Name:TETRA TMO
 Tag:SYSTEM:TETRA_TMO
 Commands:GO
 Data Type:SUBMENU
 Availability:

Option:R8-TETRA_TMO
 Typical Completion Time:2000 ms

Name:TETRA Base Station
 Tag:SYSTEM:TETRA_BST
 Commands:GO
 Data Type:SUBMENU
 Availability:

Option:R8-TETRA_BSM
 Typical Completion Time:2000 ms

Name:NXDN™ Trunk
 Tag:SYSTEM:NXDN_TRUNK
 Commands:GO
 Data Type:SUBMENU

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 13 OF 107	

Availability:

Option:R8-NXDNTYPC

Typical Completion Time:2000 ms

Name:DISPLAY Zone

Tag:SYSTEM:DISPLAY

Commands:GO

Data Type:SUBMENU

Typical Completion Time:1000 ms

Name:METER Zone

Tag:SYSTEM:METER

Commands:GO

Data Type:SUBMENU

Typical Completion Time:1000 ms

Name:State

Tag:SYSTEM:State

Commands:GET

Data Type:LIST

List Values: INIT, RUN, LOAD, CALIBRATE

Typical Completion Time:0 ms

Name:Mode

Tag:SYSTEM:Mode

Commands:GET

Data Type:LIST

List Values: Monitor, Generate, Duplex, Track Gen, Cable Fault

Typical Completion Time:0 ms

Name:Mode

Tag:SYSTEM:Mode Request

Commands:GET, SET

Data Type:LIST

List Values: Monitor, Generate, Duplex

Typical Completion Time:2000 ms

Name:Squelch Position

Tag:SYSTEM:Squelch Position

Commands:GET

Data Type:FLOAT

Typical Completion Time:0 ms

Name:Squelch State

Tag:SYSTEM:Squelch State

Commands:GET

Data Type:BOOLEAN

List Values: Squelched - Low Signal, Not Squelched

Typical Completion Time:0 ms


Name:Serial Number

Tag:SYSTEM:UNITID

Commands:GET

Data Type:STRING

Typical Completion Time:0 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 14 OF 107	

Name:

Tag:SYSTEM:BaseModel

Commands:GET

Data Type:STRING

Typical Completion Time:0 ms

Name:External Drives

Tag:SYSTEM:External Drives

Commands:GET

Data Type:LIST

List Values:

Typical Completion Time:0 ms

Name:Select Display

Tag:DISPLAY:Subzone

Commands:GET, SET

Data Type:LIST

List Values: Spec An, Mod Scope [Test Mode=Standard or Test Mode=DPMR or Test Mode=NXDN or Test Mode=NXDN Trunk], Oscilloscope [Test Mode=Standard or Test Mode=DPMR or Test Mode=NXDN or Test Mode=NXDN Trunk or Test Mode=PROJECT 25 or Test Mode=P25 Trunk or Test Mode=P25 II], Bar Graphs [Test Mode=Standard or Test Mode=DPMR or Test Mode=NXDN or Test Mode=PROJECT 25 or Test Mode=P25 II], Eye Diagram [Test Mode=DPMR or Test Mode=NXDN or Test Mode=NXDN Trunk or Test Mode=PROJECT 25 or Test Mode=P25 Trunk or Test Mode=P25 II or Test Mode=PTC-ACSES or Test Mode=PTC-ITCR], Power Profile [Test Mode=DMR or Test Mode=P25 II and P25_II:Mon Mod Type=HCPM or Test Mode=PTC-ACSES or Test Mode=PTC-ITCR or Test Mode=TETRA BST or Test Mode=TETRA DMO], General Sequence [METER:Decoder=General Sequence], Voice Frame Decode [Test Mode=PROJECT 25], Mod Spec / Constellation [Test Mode=TETRA BST or Test Mode=TETRA DMO], Constellation Plot [Test Mode=PTC-ITCR or Test Mode=PROJECT 25 and P25:Mon Mod Type=LSM or Test Mode=PROJECT 25 and P25:Mon Mod Type=WCQPSK], Distribution Plot [Test Mode=PROJECT 25 or Test Mode=P25 Trunk or Test Mode=P25 II or Test Mode=PTC-ITCR]

Availability:

Operating Mode:Monitor, Generate, Duplex

Typical Completion Time:500 ms

Name:Samples

Tag:DISPLAY:Spectral Data

Commands:GET

Data Type:ARRAY

Availability:

Operating Mode:Monitor, Duplex, Track Gen

Typical Completion Time:100 ms

Name:Samples

Tag:DISPLAY:Demodulation Data

Commands:GET


Data Type:ARRAY

Availability:

Operating Mode:Monitor, Duplex

Typical Completion Time:100 ms

Name:Samples

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 15 OF 107	

Tag:DISPLAY:Modulation Data

Commands:GET

Data Type:ARRAY

Availability:

Operating Mode:Generate, Duplex

Typical Completion Time:100 ms

Name:Samples

Tag:DISPLAY:External Data

Commands:GET

Data Type:ARRAY

Availability:

Operating Mode:Monitor, Generate, Duplex

Typical Completion Time:100 ms

Name:Center Frequency

Tag:DISPLAY:Monitor Frequency

Commands:GET, SET

Data Type:FLOAT

Range: 250000 Hz to 1000000000 Hz

Units: Hz, kHz, MHz, GHz

Availability:

Operating Mode:Monitor, Duplex

Menu:DISPLAY:Subzone=Spec An

Typical Completion Time:5000 ms

Name:Span

Tag:DISPLAY:Span

Commands:GET, SET

Data Type:FLOAT

Range: 9751 Hz to 1000000000 Hz

Units: Hz, kHz, MHz, GHz

Availability:

Operating Mode:Monitor, Duplex

Menu:DISPLAY:Subzone=Spec An

Typical Completion Time:5000 ms

Name:Start Frequency

Tag:DISPLAY:Start Frequency

Commands:GET, SET

Data Type:FLOAT

Range: 250000 Hz to 1000000000 Hz

Units: Hz, kHz, MHz, GHz

Availability:

Operating Mode:Monitor, Duplex

Menu:DISPLAY:Subzone=Spec An

Typical Completion Time:5000 ms

Name:Stop Frequency

Tag:DISPLAY:Stop Frequency


Commands:GET, SET

Data Type:FLOAT

Range: 250000 Hz to 1000000000 Hz

Units: Hz, kHz, MHz, GHz

Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 16 OF 107	

Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Spec An
 Typical Completion Time:5000 ms

Name:See and Hear Active

Tag:DISPLAY:SNH Active

Commands:GET

Data Type:BOOLEAN

List Values:

Availability:

Menu:DISPLAY:Subzone=Spec An

Typical Completion Time:0 ms

Name:Resolution Bandwidth

Tag:DISPLAY:Resolution Bandwidth

Commands:GET

Data Type:FLOAT

Availability:

Menu:DISPLAY:Subzone=Spec An

Typical Completion Time:0 ms

Name:Reference Level (dBm)

Tag:DISPLAY:Reference Level

Commands:GET, SET

Data Type:INTEGER

Range: 0 to 90

Availability:

Operating Mode:Monitor, Duplex

Menu:DISPLAY:Subzone=Spec An

Typical Completion Time:100 ms

Name:Vertical Scale

Tag:DISPLAY:Vertical Scale

Commands:GET, SET

Data Type:LIST

List Values: 10 dB/div, 5 dB/div, 2 dB/div, 1 dB/div

Availability:

Operating Mode:Monitor, Duplex

Option:R8-ESA

Menu:DISPLAY:Subzone=Spec An

Typical Completion Time:100 ms

Name:Display Mode

Tag:DISPLAY:Display Mode

Commands:GET, SET

Data Type:LIST

List Values: Normal, Freeze, Max Hold, Average

Availability:

Operating Mode:Monitor, Duplex

Menu:DISPLAY:Subzone=Spec An

Typical Completion Time:100 ms

Name:Trace Math

Tag:DISPLAY:Trace Math

Commands:GET, SET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 17 OF 107	

Data Type:LIST
 List Values: None, Spec-Ref (log),
 Spec-Ref
 (lin), Spec+Ref (lin)
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Spec An
 Typical Completion Time:100 ms


Name:Set Reference Trace
 Tag:DISPLAY:Set Reference Trace
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Spec An
 Typical Completion Time:100 ms

Name:Detector
 Tag:DISPLAY:Detector
 Commands:GET, SET
 Data Type:LIST
 List Values: Power, Peak, Sample, Mean, Valley
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Spec An
 Typical Completion Time:200 ms

Name:Coupling
 Tag:DISPLAY:Coupling
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: DC, AC
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Oscilloscope
 Typical Completion Time:500 ms

Name:Horizontal Scale
 Tag:DISPLAY:Horizontal Scale
 Commands:GET, SET
 Data Type:LIST
 List Values: 20 us, 50 us, 100 us, 200 us, 500 us, 1 ms, 2 ms, 5 ms, 10 ms,
 20 ms, 50 ms, 100 ms, 200 ms, 500 ms, 1 s
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Mod Scope
 Typical Completion Time:100 ms

Name:Horizontal Scale
 Tag:DISPLAY:Ext Horizontal Scale
 Commands:GET, SET
 Data Type:LIST
 List Values: 20 us (Max 50 kHz In), 50 us (Max 20 kHz In), 100 us (Max 10 kHz
 In), 200 us (Max 5 kHz In), 500 us (Max 2 kHz In), 1 ms (Max 1 kHz In), 2 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 18 OF 107	

(Max 500 Hz In), 5 ms (Max 200 Hz In), 10 ms (Max 100 Hz In), 20 ms (Max 50 Hz In), 50 ms (Max 20 Hz In), 100 ms (Max 10 Hz In), 200 ms (Max 5 Hz In), 500 ms (Max 2 Hz In), 1 s (Max 1 Hz In)

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:DISPLAY:Subzone=Oscilloscope

Typical Completion Time:500 ms

Name:Vertical Scale

Tag:DISPLAY:AM Vertical Scale

Commands:GET, SET

Data Type:LIST

List Values: 1%, 2%, 5%, 10%, 20%, 50%

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:DISPLAY:Subzone=Mod Scope

Typical Completion Time:100 ms

Name:Vertical Scale

Tag:DISPLAY:FM Vertical Scale

Commands:GET, SET

Data Type:LIST

List Values: 100 Hz, 200 Hz, 500 Hz, 1 kHz, 2 kHz, 5 kHz, 10 kHz, 20 kHz, 50 kHz

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:DISPLAY:Subzone=Mod Scope

Typical Completion Time:100 ms

Name:Vertical Scale

Tag:DISPLAY:Ext Vertical Scale

Commands:GET, SET

Data Type:LIST

List Values: 50 mV, 100 mV, 200 mV, 500 mV, 1 V, 2 V, 5 V, 10 V, 15 V, 20 V, 25 V

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:DISPLAY:Subzone=Oscilloscope

Typical Completion Time:500 ms

Name:Find Peak

Tag:DISPLAY:Find Peak

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Monitor, Duplex

Menu:DISPLAY:Subzone=Spec An

Typical Completion Time:100 ms

Name:Center Peak


Tag:DISPLAY:Center Peak

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Monitor, Duplex

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 19 OF 107	

Menu:DISPLAY:Subzone=Spec An
 Typical Completion Time:5000 ms

Name:Trigger Mode
 Tag:DISPLAY:Trigger
 Commands:GET, SET
 Data Type:LIST
 List Values: Auto, Normal, Single
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Mod Scope
 Typical Completion Time:100 ms


Name:Trigger Level
 Tag:DISPLAY:Trigger Level
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 200000
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Mod Scope
 Typical Completion Time:100 ms

Name:Trigger Level (%)
 Tag:DISPLAY:AM Trigger Level
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 99
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Mod Scope
 Typical Completion Time:100 ms

Name:Trigger Edge
 Tag:DISPLAY:Trigger Edge
 Commands:GET, SET
 Data Type:LIST
 List Values: Rising, Falling, Either
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Mod Scope
 Typical Completion Time:100 ms

Name:Scope Mode
 Tag:DISPLAY:Mod Scope Select
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Monitor, Generate
 Availability:
 Operating Mode:Duplex
 Menu:DISPLAY:Subzone=Mod Scope
 Typical Completion Time:100 ms

Name:Trigger Mode
 Tag:DISPLAY:Ext Trigger

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 20 OF 107	

Commands:GET, SET
 Data Type:LIST
 List Values: Auto, Normal, Single, Freeze
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Oscilloscope
 Typical Completion Time:500 ms


Name:Trigger Level
 Tag:DISPLAY:Ext Trigger Level
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Oscilloscope
 Typical Completion Time:500 ms

Name:Trigger Position
 Tag:DISPLAY:Ext Trigger Position
 Commands:GET, SET
 Data Type:LIST
 List Values: 10%, 50%, 90%
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Oscilloscope
 Typical Completion Time:500 ms

Name:Trigger Edge
 Tag:DISPLAY:Ext Trigger Edge
 Commands:GET, SET
 Data Type:LIST
 List Values: Rising, Falling, Either
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:DISPLAY:Subzone=Oscilloscope
 Typical Completion Time:500 ms

Name:Deviation Average
 Tag:DISPLAY:Deviation Average
 Commands:GET, SET
 Data Type:LIST
 List Values: Normal, Peak Average [Test Mode=Standard], Pwr-Weight Average [Test Mode=Standard], RMS Average [Test Mode=Standard], +/-Peak / 2 [Test Mode=Standard]
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Bar Graphs
 Typical Completion Time:100 ms

Name:Display Mode
 Tag:DISPLAY:Eye Display Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Normal, Fade Away

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 21 OF 107	

Availability:

Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Eye Diagram

Typical Completion Time:100 ms

Name:Decode to Standard

Tag:DISPLAY:Standard

Commands:GET, SET

Data Type:LIST

List Values: None, CCIR1, CCIR2, PCCIR, CCITT, EEA, EIA, Euro, NATEL, MODAT, ZVEI1, ZVEI2, ZVEI3, PZVEI, DZVEI, PDZVEI

Availability:

Menu:DISPLAY:Subzone=General Sequence

Typical Completion Time:100 ms

Name>Select View

Tag:DISPLAY>Select View

Commands:GET, SET

Data Type:LIST

List Values: Current [Test Mode=DMR], Alternate [Test Mode=DMR], Both [Test Mode=DMR], Frame [Test Mode=P25 II or Test Mode=TETRA DMO], Slot 1 [Test Mode=P25 II or Test Mode=TETRA DMO], Slot 2 [Test Mode=P25 II]

Availability:

Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Power Profile

Typical Completion Time:100 ms

Name>Select Frame

Tag:DISPLAY:Frame

Commands:GET, SET

Data Type:LIST

List Values: 1, 2, 3, 4, 5, 6

Availability:

Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Power Profile

Typical Completion Time:100 ms

Name:Vertical Maximum (dBm)

Tag:DISPLAY:PP Vertical Maximum

Commands:GET, SET

Data Type:INTEGER

Range: 0 to 60

Availability:

Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Power Profile

Typical Completion Time:100 ms

Name:Vertical Scale

Tag:DISPLAY:PP Vertical Scale


Commands:GET, SET

Data Type:LIST

List Values: 10 dB/div, 5 dB/div, 2 dB/div, 1 dB/div

Availability:

Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Power Profile

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 22 OF 107	

Typical Completion Time:100 ms

Name:Horizontal Start (ms)
 Tag:DISPLAY:PP Horizontal Start
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 6000
 Availability:
 Operating Mode:Monitor, Duplex
 Option:R8-PTC_ACSES
 Menu:DISPLAY:Subzone=Power Profile
 Typical Completion Time:100 ms


Name:Horizontal Maximum (ms)
 Tag:DISPLAY:PP Horizontal Maximum
 Commands:GET, SET
 Data Type:INTEGER
 Range: 20 to 500
 Availability:
 Operating Mode:Monitor, Duplex
 Option:R8-PTC_ACSES, R8-PTC_ITCR
 Menu:DISPLAY:Subzone=Power Profile
 Typical Completion Time:100 ms

Name:Power Profile before Display Mode
 Tag:DISPLAY:Power Profile Data
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Power Profile
 Typical Completion Time:100 ms

Name:Display Mode
 Tag:DISPLAY:PP Display Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Normal, Freeze, Max Hold, Average
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Power Profile
 Typical Completion Time:100 ms

Name:Power Profile after Display Mode
 Tag:DISPLAY:Power Profile
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Power Profile
 Typical Completion Time:100 ms

Name:Update Power Profile
 Tag:DISPLAY:Power Profile Request
 Commands:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 23 OF 107	

Data Type:BOOLEAN
 List Values: F, T
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DISPLAY:Subzone=Power Profile
 Typical Completion Time:100 ms


Name:
 Tag:DISPLAY:Distribution Data
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:1100 ms

Name:Constellation Data
 Tag:DISPLAY:Constellation Data
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:100 ms

Name:Select Meter
 Tag:METER:Subzone
 Commands:GET, SET
 Data Type:LIST
 List Values: Power Meter [Test Mode=Standard or Test Mode=DMR or Test Mode=DPMR or Test Mode=NXDN or Test Mode=PROJECT 25 or Test Mode=P25 II], Voltmeter [Test Mode=Standard or Test Mode=DMR or Test Mode=DPMR or Test Mode=NXDN or Test Mode=PROJECT 25 or Test Mode=P25 II or Test Mode=TETRA DMO], SINAD/Distortion [Test Mode=Standard], Decoder [Test Mode=Standard or Test Mode=PROJECT 25], Frequency Counter [Test Mode=Standard], P25 Trunking [Test Mode=P25 Trunk], Constellation [Test Mode=DMR or Test Mode=P25 II or Test Mode=PTC-ACSES or Test Mode=PTC-ITCR], RF Scan [Test Mode=Standard or Test Mode=DMR or Test Mode=DPMR or Test Mode=NXDN or Test Mode=PROJECT 25], NXDN™ Trunking [Test Mode=NXDN Trunk]
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Typical Completion Time:100 ms

Name:Reset Meter Fields
 Tag:METER:Reset Meter Fields
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Duplex
 Menu:METER:Subzone=P25 Trunking
 Typical Completion Time:100 ms

Name:Range
 Tag:METER:PWR Meter Range
 Commands:GET, SET
 Data Type:LIST
 List Values: 5W, 10W, 50W, 150W

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 24 OF 107	

Availability:

Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=Power Meter

Typical Completion Time:100 ms

Name:Measured Power

Tag:METER:Measured Power

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor, Duplex
 Menu:METER:Subzone=Power Meter

Typical Completion Time:0 ms

Name:Select Voltmeter Mode

Tag:METER:Voltmeter

Commands:GET, SET

Data Type:LIST

List Values: AC Volts [Test Mode=Standard or Test Mode=DMR or Test Mode=DPMR or Test Mode=NXDN or Test Mode=PROJECT 25 or Test Mode=P25 II or Test Mode=TETRA DMO], DC Volts [Test Mode=Standard or Test Mode=DMR or Test Mode=DPMR or Test Mode=NXDN or Test Mode=PROJECT 25 or Test Mode=P25 II or Test Mode=TETRA DMO]

Availability:

Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=Voltmeter

Typical Completion Time:100 ms

Name:AC Range

Tag:METER:AC Range

Commands:GET, SET

Data Type:LIST

List Values: Auto, 1 V, 10 V, 70 V

Availability:

Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=Voltmeter

Typical Completion Time:100 ms

Name:Set dBr Reference

Tag:METER:Set Reference

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=Voltmeter

Typical Completion Time:100 ms

Name:Clear dBr Reference

Tag:METER:Clear Reference

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=Voltmeter

Typical Completion Time:100 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 25 OF 107	

Name:DC Range
 Tag:METER:DC Range
 Commands:GET, SET
 Data Type:LIST
 List Values: Auto, 1 V, 10 V, 100 V
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=Voltmeter
 Typical Completion Time:100 ms


Name:AC Volts
 Tag:METER:AC Volts
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=Voltmeter
 Typical Completion Time:0 ms

Name:DC Volts
 Tag:METER:DC Volts
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=Voltmeter
 Typical Completion Time:0 ms

Name:Select Audio Measurement
 Tag:METER:Audio Meter
 Commands:GET, SET
 Data Type:LIST
 List Values: SINAD/Ext Distortion [Test Mode=Standard], Internal Distortion [Test Mode=Standard]
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=SINAD/Distortion
 Typical Completion Time:100 ms

Name:SINAD
 Tag:METER:SINAD
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=SINAD/Distortion
 Typical Completion Time:0 ms

Name:External Distortion
 Tag:METER:External Distortion
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Generate, Duplex

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 26 OF 107	

Menu:METER:Subzone=SINAD/Distortion

Typical Completion Time:0 ms

Name:Internal Distortion

Tag:METER:Internal Distortion

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:METER:Subzone=SINAD/Distortion

Typical Completion Time:0 ms

Name:Select Decoder Type

Tag:METER:Decoder

Commands:GET, SET

Data Type:LIST

List Values: PL/Period Counter [Test Mode=Standard], DPL Decode [Test Mode=Standard], DTMF Decode [Test Mode=Standard], 2-Tone Decode [Test Mode=Standard], 5/6 Tone Decode [Test Mode=Standard], General Sequence [Test Mode=Standard], Voice Frame Decode [Test Mode=PROJECT 25]

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:100 ms

Name:Reset

Tag:METER:Reset

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:METER:Subzone=Decoder, Frequency Counter

Typical Completion Time:100 ms

Name:PL Freq

Tag:METER:PL Frequency

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:PL Code

Tag:METER:PL Code

Commands:GET

Data Type:STRING

Availability:

Operating Mode:Monitor, Duplex


Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:DPL Code

Tag:METER:DPL Code

Commands:GET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 27 OF 107	

Data Type:STRING

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:DTMF Code

Tag:METER:DTMF Code

Commands:GET

Data Type:STRING

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:General Sequence Decodes

Tag:METER:GenSeqDecodes

Commands:GET

Data Type:ARRAY

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:Decode

Tag:METER:Decode

Commands:GET, SET

Data Type:LIST

List Values: Stop, Start

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:500 ms

Name:Code Sequence

Tag:METER:Code Sequence

Commands:GET, SET

Data Type:STRING

Format:(GENSEQCode)

char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, E, F, G, H, I, J

Availability:

Operating Mode:Duplex

Typical Completion Time:100 ms

Name:Decode Burst

Tag:METER:Decode Burst

Commands:DO

Data Type:FUNCTION

Availability:


Operating Mode:Duplex

Typical Completion Time:500 ms

Name:Tone1 Freq.

Tag:METER:Tone1 Freq

Commands:GET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 28 OF 107	

Data Type:FLOAT

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:Tone1 Duration

Tag:METER:Tone1 Duration

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:Tone2 Freq.

Tag:METER:Tone2 Freq

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:Tone2 Duration

Tag:METER:Tone2 Duration

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:5/6 Codes

Tag:METER:56_Codes

Commands:GET

Data Type:STRING

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:0 ms

Name:5/6 Freqs

Tag:METER:56_Freqs

Commands:GET

Data Type:ARRAY

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder


Typical Completion Time:100 ms

Name:5/6 Durations

Tag:METER:56_Durs

Commands:GET

Data Type:ARRAY

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 29 OF 107	

Availability:

Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:100 ms

Name:Decode to Standard

Tag:METER:Standard

Commands:GET, SET

Data Type:LIST

List Values: None, CCIR1, CCIR2, PCCIR, CCITT, EEA, EIA, Euro, NATEL, MODAT, ZVEI1, ZVEI2, ZVEI3, PZVEI, DZVEI, PDZVEI

Availability:

Menu:METER:Subzone=Decoder

Typical Completion Time:500 ms

Name:High Pass Filter

Tag:METER:High Pass Filter

Commands:GET, SET

Data Type:LIST

List Values: 1 Hz, 300 Hz, 3 kHz

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:100 ms

Name:Low Pass Filter

Tag:METER:Low Pass Filter

Commands:GET, SET

Data Type:LIST

List Values: 300 Hz, 3 kHz, 20 kHz

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:METER:Subzone=Decoder

Typical Completion Time:100 ms

Name:Input Decoding

Tag:METER:Input Decoding

Commands:GET, SET

Data Type:BOOLEAN

List Values: Internal, External

Availability:

Menu:METER:Subzone=Decoder, Frequency Counter

Typical Completion Time:100 ms

Name:Frequency Counter

Tag:METER:Frequency Counter

Commands:GET

Data Type:FLOAT

Availability:


Operating Mode:Monitor, Duplex

Menu:METER:Subzone=Frequency Counter

Typical Completion Time:0 ms

Name:Resolution

Tag:METER:Resolution

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 30 OF 107	

Commands:GET, SET
 Data Type:LIST
 List Values: 0.001 Hz, 0.01 Hz, 0.1 Hz, 1.0 Hz, 10 Hz
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:METER:Subzone=Frequency Counter
 Typical Completion Time:100 ms


Name:Test Status
 Tag:METER:Trunk Status
 Commands:GET
 Data Type:STRING
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:METER:Subzone=P25 Trunking
 Typical Completion Time:0 ms

Name:Deviations
 Tag:METER:Constellation
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:100 ms

Name:Start Frequency (MHz)
 Tag:METER:Start Frequency
 Commands:GET, SET
 Data Type:INTEGER
 Range: 1 to 3000
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:METER:Subzone=RF Scan
 Typical Completion Time:5000 ms

Name:Stop Frequency (MHz)
 Tag:METER:Stop Frequency
 Commands:GET, SET
 Data Type:INTEGER
 Range: 1 to 3000
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:METER:Subzone=RF Scan
 Typical Completion Time:5000 ms

Name:Scan
 Tag:METER:Run RF Scan
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Single, Auto
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:METER:Subzone=RF Scan
 Typical Completion Time:100 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 31 OF 107	

Name:RF Scan State
 Tag:METER:RF Scan State
 Commands:GET
 Data Type:LIST
 List Values: Disabled, Scanning, Locked, Inactive
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:METER:Subzone=RF Scan
 Typical Completion Time:0 ms


Name:Spectrum
 Tag:METER:RF Scan Data
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:METER:Subzone=RF Scan
 Typical Completion Time:0 ms

Name:Test Status
 Tag:METER:NXDN Trunk Status
 Commands:GET
 Data Type:STRING
 Availability:
 Operating Mode:Duplex
 Menu:METER:Subzone=NXDN™ Trunking
 Typical Completion Time:0 ms

Name:Toggle with DO RF:RF Power
 Tag:RF:RF Power
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Off, On
 Availability:
 Operating Mode:Generate, Duplex
 Typical Completion Time:100 ms

Name:Monitor Frequency
 Tag:RF:Monitor Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:5000 ms

Name:Copy Frequency to Generator
 Tag:RF:Copy Mon to Gen
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Monitor
 Typical Completion Time:5000 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 32 OF 107	

Name:Generate Frequency
 Tag:RF:Generate Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Generate, Duplex
 Typical Completion Time:5000 ms


Name:Copy Frequency to Monitor
 Tag:RF:Copy Gen to Mon
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Generate
 Typical Completion Time:5000 ms

Name:Modulation Type
 Tag:RF:Modulation Type
 Commands:GET, SET
 Data Type:LIST
 List Values: FM [Test Mode=Standard], AM [Test Mode=Standard], USB [Test Mode=Standard and Option=R8-SSB], LSB [Test Mode=Standard and Option=R8-SSB], 4FSK [Test Mode=DMR or Test Mode=DPMR or Test Mode=NXDN], GMSK~ [Test Mode=PTC-ACSES], C4FM [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], LSM [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], WCQPSK [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], pi/4 DQPSK [Test Mode=PTC-ITCR or Test Mode=TETRA DMO or Test Mode=TETRA TMO or Test Mode=TETRA BST], HCPM [Test Mode=P25 II], HDQPSK [Test Mode=P25 II and Operating Mode=Monitor or Test Mode=P25 II and Operating Mode=Generate]
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Typical Completion Time:100 ms

Name:Output Level (dBm)
 Tag:RF:Output Level
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 5
 Availability:
 Operating Mode:Generate, Duplex
 Typical Completion Time:500 ms

Name:Gen Port
 Tag:RF:Generate Port
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: RF In/Out, Gen Out
 Availability:
 Operating Mode:Generate, Duplex
 Typical Completion Time:500 ms

Name:Bandwidth
 Tag:RF:Bandwidth

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 33 OF 107	

Commands:GET, SET
 Data Type:LIST
 List Values: 6.25 kHz (Narrow), 12.5 kHz (Narrow), 25 kHz (Wide), 50 kHz (Wide), 100 kHz (Wide), 200 kHz (Wide)
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Typical Completion Time:100 ms

Name:Attenuation
 Tag:RF:Attenuation
 Commands:GET, SET
 Data Type:LIST
 List Values: 0 dB, 2 dB, 4 dB, 6 dB, 8 dB, 10 dB, 12 dB, 14 dB, 16 dB, 18 dB, 20 dB, 22 dB, 24 dB, 26 dB, 28 dB, 30 dB, 32 dB, 34 dB, 36 dB, 38 dB, 40 dB, 42 dB, 44 dB, 46 dB, 48 dB, 50 dB, 52 dB, 54 dB, 56 dB, 58 dB, 60 dB, 62 dB
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:500 ms


Name:Pre-Amplifier
 Tag:RF:PreAmp On
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Off, On
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:500 ms

Name:Mon Port
 Tag:RF:Monitor Port
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: RF In/Out, Antenna
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:500 ms

Name:Receiver Overload
 Tag:RF:RX Overload
 Commands:GET
 Data Type:BOOLEAN
 List Values: Okay, Receiver Overload - Increase Attenuation
 Typical Completion Time:0 ms

Name:Mod Port Mode
 Tag:AUDIO:Mod Port
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: In, Out
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Fixed 1kHz Level (V)

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 34 OF 107	

Tag:AUDIO:Fixed 1kHz
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 8
 Availability:
 Operating Mode:Monitor
 Menu:AUDIO
 Typical Completion Time:100 ms


Name:Fixed 1kHz Level (kHz)
 Tag:AUDIO:Gen Fixed 1kHz
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Fixed 1kHz Level (%AM)
 Tag:AUDIO:Gen AM Fixed 1kHz
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 99
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Fixed 1kHz Mode
 Tag:AUDIO:Fixed 1kHz Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Synth Level (V)
 Tag:AUDIO:Synth
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 8
 Availability:
 Operating Mode:Monitor
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Synth Level (kHz)
 Tag:AUDIO:Gen Synth
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 35 OF 107	

Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Synth Level (%AM)
 Tag:AUDIO:Gen AM Synth
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 99
 Availability:

Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Format
 Tag:AUDIO:Format
 Commands:GET, SET
 Data Type:LIST
 List Values: PL, DPL, DPL Invert, A/B Sequence, 5/6 Tone, POCSAG, General Sequence
 Availability:

Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:1000 ms


Name:Synth Mode
 Tag:AUDIO:Synth Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous, Burst [AUDIO:Format=A/B Sequence or AUDIO:Format=5/6 Tone or AUDIO:Format=POCSAG or AUDIO:Format=General Sequence], Disconnect Tone [AUDIO:Format=DPL or AUDIO:Format=DPL Invert]
 Availability:

Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:500 ms

Name:PL Code
 Tag:AUDIO:PL Code
 Commands:GET, SET
 Data Type:LIST
 List Values: XZ, WZ, XA, WA, XB, WB, YZ, YA, YB, ZZ, ZA, ZB, 1Z, 1A, 1B, 2Z, 2A, 2B, 3Z, 3A, 3B, 4Z, 4A, 4B, 5Z, 5A, 5B, 6Z, 6A, 6B, 7Z, 7A, M1, 8Z, M2, M3, M4, 9Z, M5, M6, M7
 Availability:

Synth Format:PL
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:PL Frequency (Hz)
 Tag:AUDIO:PL Frequency
 Commands:GET
 Data Type:FLOAT
 Range: 0 to 999

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 36 OF 107	

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:AUDIO

Typical Completion Time:100 ms

Name:PL Table

Tag:AUDIO:PL Table

Commands:GO

Data Type:SUBMENU

Availability:

Synth Format:PL

Operating Mode:Monitor, Generate, Duplex

Menu:AUDIO

Typical Completion Time:2000 ms

Name:DPL Code


Tag:AUDIO:DPL Code

Commands:GET, SET

Data Type:LIST

List Values: 000, 001, 002, 003, 004, 005, 006, 007, 010, 011, 012, 013, 014, 015, 016, 017, 020, 021, 022, 023, 024, 025, 026, 027, 030, 031, 032, 033, 034, 035, 036, 037, 040, 041, 042, 043, 044, 045, 046, 047, 050, 051, 052, 053, 054, 055, 056, 057, 060, 061, 062, 063, 064, 065, 066, 067, 070, 071, 072, 073, 074, 075, 076, 077, 100, 101, 102, 103, 104, 105, 106, 107, 110, 111, 112, 113, 114, 115, 116, 117, 120, 121, 122, 123, 124, 125, 126, 127, 130, 131, 132, 133, 134, 135, 136, 137, 140, 141, 142, 143, 144, 145, 146, 147, 150, 151, 152, 153, 154, 155, 156, 157, 160, 161, 162, 163, 164, 165, 166, 167, 170, 171, 172, 173, 174, 175, 176, 177, 200, 201, 202, 203, 204, 205, 206, 207, 210, 211, 212, 213, 214, 215, 216, 217, 220, 221, 222, 223, 224, 225, 226, 227, 230, 231, 232, 233, 234, 235, 236, 237, 240, 241, 242, 243, 244, 245, 246, 247, 250, 251, 252, 253, 254, 255, 256, 257, 260, 261, 262, 263, 264, 265, 266, 267, 270, 271, 272, 273, 274, 275, 276, 277, 300, 301, 302, 303, 304, 305, 306, 307, 310, 311, 312, 313, 314, 315, 316, 317, 320, 321, 322, 323, 324, 325, 326, 327, 330, 331, 332, 333, 334, 335, 336, 337, 340, 341, 342, 343, 344, 345, 346, 347, 350, 351, 352, 353, 354, 355, 356, 357, 360, 361, 362, 363, 364, 365, 366, 367, 370, 371, 372, 373, 374, 375, 376, 377, 400, 401, 402, 403, 404, 405, 406, 407, 410, 411, 412, 413, 414, 415, 416, 417, 420, 421, 422, 423, 424, 425, 426, 427, 430, 431, 432, 433, 434, 435, 436, 437, 440, 441, 442, 443, 444, 445, 446, 447, 450, 451, 452, 453, 454, 455, 456, 457, 460, 461, 462, 463, 464, 465, 466, 467, 470, 471, 472, 473, 474, 475, 476, 477, 500, 501, 502, 503, 504, 505, 506, 507, 510, 511, 512, 513, 514, 515, 516, 517, 520, 521, 522, 523, 524, 525, 526, 527, 530, 531, 532, 533, 534, 535, 536, 537, 540, 541, 542, 543, 544, 545, 546, 547, 550, 551, 552, 553, 554, 555, 556, 557, 560, 561, 562, 563, 564, 565, 566, 567, 570, 571, 572, 573, 574, 575, 576, 577, 600, 601, 602, 603, 604, 605, 606, 607, 610, 611, 612, 613, 614, 615, 616, 617, 620, 621, 622, 623, 624, 625, 626, 627, 630, 631, 632, 633, 634, 635, 636, 637, 640, 641, 642, 643, 644, 645, 646, 647, 650, 651, 652, 653, 654, 655, 656, 657, 660, 661, 662, 663, 664, 665, 666, 667, 670, 671, 672, 673, 674, 675, 676, 677, 700, 701, 702, 703, 704, 705, 706, 707, 710, 711, 712, 713, 714, 715, 716, 717, 720, 721, 722, 723, 724, 725, 726, 727, 730, 731, 732, 733, 734, 735, 736, 737, 740, 741, 742, 743, 744, 745, 746, 747, 750, 751, 752, 753, 754, 755, 756, 757, 760, 761, 762, 763, 764, 765, 766, 767, 770, 771, 772, 773, 774, 775, 776, 777

Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 37 OF 107	

Synth Format:DPL, DPL Invert
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms


Name:A/B Sequence
 Tag:AUDIO:Sequence
 Commands:GET, SET
 Data Type:LIST
 List Values: 1, 2, 3, 4
 Availability:
 Synth Format:A/B Sequence
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Code Sequence
 Tag:AUDIO:Code Sequence
 Commands:GET, SET
 Data Type:STRING
 Format:(GENSEQCode)
 char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, E, F, G, H, I, J
 Availability:
 Synth Format:General Sequence
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:A/B Sequence Table
 Tag:AUDIO:SEQUENCE Table
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Synth Format:A/B Sequence
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:2000 ms

Name:General Sequence Table
 Tag:AUDIO:GENSEQ Table
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Synth Format:General Sequence
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:2000 ms

Name:5/6 Tone
 Tag:AUDIO:5/6 Tone
 Commands:GET, SET
 Data Type:STRING
 Format:(56Tone)
 char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9
 Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 38 OF 107	

Synth Format:5/6 Tone
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms


Name:POCSAG Message
 Tag:AUDIO:POCSAG Message
 Commands:GET, SET
 Data Type:LIST
 List Values: Tone Only, NumericNum, NumericSet, AlphaNumUC, AlphaNumLC,
 AlphaNumSP, NumericCust, AlphaNumCust
 Availability:
 Synth Format:POCSAG
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:POCSAG Table
 Tag:AUDIO:POCSAG Table
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Synth Format:POCSAG
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:2000 ms

Name:Tone A Level (V)
 Tag:AUDIO:Tone A
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 8
 Availability:
 Operating Mode:Monitor
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone A Level (kHz)
 Tag:AUDIO:Gen Tone A
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone A Level (%AM)
 Tag:AUDIO:Gen AM Tone A
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 99
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 39 OF 107	

Typical Completion Time:100 ms

Name:Tone A Frequency (Hz)
 Tag:AUDIO:Tone A Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 20000
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms


Name:Tone A Mode
 Tag:AUDIO:Tone A Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous, Burst
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone B Level (V)
 Tag:AUDIO:Tone B
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 8
 Availability:
 Operating Mode:Monitor
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone B Level (kHz)
 Tag:AUDIO:Gen Tone B
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone B Level (%AM)
 Tag:AUDIO:Gen AM Tone B
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 99
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone B Frequency (Hz)
 Tag:AUDIO:Tone B Frequency
 Commands:GET, SET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 40 OF 107	

Data Type:FLOAT
 Range: 0 to 20000
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms


Name:Tone B Mode
 Tag:AUDIO:Tone B Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous, Burst
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone C Level (kHz)
 Tag:AUDIO:Gen Tone C
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone C Level (%AM)
 Tag:AUDIO:Gen AM Tone C
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 99
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone C Frequency (Hz)
 Tag:AUDIO:Tone C Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 100000
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Tone C Mode
 Tag:AUDIO:Tone C Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 41 OF 107	

Typical Completion Time:100 ms

Name:DTMF Level (V)

Tag:AUDIO:DTMF

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 8

Availability:

Operating Mode:Monitor

Menu:AUDIO

Typical Completion Time:100 ms

Name:DTMF Level (kHz)

Tag:AUDIO:Gen DTMF

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 100

Availability:

Operating Mode:Generate, Duplex

Menu:AUDIO

Typical Completion Time:100 ms

Name:DTMF Level (%AM)

Tag:AUDIO:Gen AM DTMF

Commands:GET, SET

Data Type:INTEGER

Range: 0 to 99

Availability:

Operating Mode:Generate, Duplex

Menu:AUDIO

Typical Completion Time:100 ms

Name:DTMF Mode

Tag:AUDIO:DTMF Mode

Commands:GET, SET

Data Type:LIST

List Values: Off, Continuous, Burst

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:AUDIO

Typical Completion Time:500 ms

Name:DTMF Code

Tag:AUDIO:DTMF Code

Commands:GET, SET

Data Type:STRING

Format:(DTMFCode)

char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, #, *

Availability:


Operating Mode:Monitor, Generate, Duplex

Menu:AUDIO

Typical Completion Time:100 ms

Name:DTMF Table

Tag:AUDIO:DTMF Table

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 42 OF 107	

Commands:GO
 Data Type:SUBMENU
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:2000 ms


Name:Microphone Mode
 Tag:AUDIO:Microphone Mode
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Off, Continuous
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:500 ms

Name:Microphone Level (V)
 Tag:AUDIO:Microphone
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 8
 Availability:
 Operating Mode:Monitor
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Microphone Level (kHz)
 Tag:AUDIO:Gen Microphone
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Microphone Level (%AM)
 Tag:AUDIO:Gen AM Microphone
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 99
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Mod In Port Level (kHz)
 Tag:AUDIO:Gen Mod In Level
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 43 OF 107	

Typical Completion Time:100 ms

Name:Mod In Port Level (%AM)
 Tag:AUDIO:Gen AM Mod In Level
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 99
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms


Name:Mod In Port Mode
 Tag:AUDIO:Mod In Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous
 Availability:
 Operating Mode:Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:High Pass Filter
 Tag:AUDIO:High Pass Filter
 Commands:GET, SET
 Data Type:LIST
 List Values: 1 Hz, 300 Hz, 3 kHz
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Low Pass Filter
 Tag:AUDIO:Low Pass Filter
 Commands:GET, SET
 Data Type:LIST
 List Values: 300 Hz, 3 kHz, 20 kHz
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:AUDIO
 Typical Completion Time:100 ms

Name:Audio Sum
 Tag:AUDIO:Audio Sum
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor
 Menu:AUDIO
 Typical Completion Time:0 ms

Name:Mod Sum
 Tag:AUDIO:Mod Sum
 Commands:GET
 Data Type:FLOAT

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 44 OF 107	

Availability:

Operating Mode:Generate, Duplex
Menu:AUDIO

Typical Completion Time:0 ms

Name:AM Mod Sum

Tag:AUDIO:AM Mod Sum

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Generate, Duplex
Menu:AUDIO

Typical Completion Time:0 ms

Name:PL Code

Tag:PL:PL Code

Commands:GET, SET

Data Type:LIST

List Values: XZ, WZ, XA, WA, XB, WB, YZ, YA, YB, ZZ, ZA, ZB, 1Z, 1A, 1B, 2Z, 2A, 2B, 3Z, 3A, 3B, 4Z, 4A, 4B, 5Z, 5A, 5B, 6Z, 6A, 6B, 7Z, 7A, M1, 8Z, M2, M3, M4, 9Z, M5, M6, M7

Availability:

Operating Mode:Monitor, Generate, Duplex
Menu:PL

Typical Completion Time:100 ms

Name:DTMF Code

Tag:DTMF:DTMF Code

Commands:GET, SET

Data Type:STRING

Format:(DTMFCode)

char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, #, *

Availability:

Menu:DTMF

Typical Completion Time:100 ms

Name:Tone Duration (ms)

Tag:DTMF:Duration

Commands:GET, SET

Data Type:INTEGER

Range: 70 to 9999

Availability:

Menu:DTMF

Typical Completion Time:100 ms

Name:Inter-digit Delay (ms)

Tag:DTMF:Delay

Commands:GET, SET

Data Type:INTEGER


Range: 70 to 9999

Availability:

Menu:DTMF

Typical Completion Time:100 ms

Name:Sequence

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 45 OF 107	

Tag:SEQUENCE:Sequence

Commands:GET, SET

Data Type:LIST

List Values: 1, 2, 3, 4

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Sequence 3 Tone A Duration (sec)

Tag:SEQUENCE:S3 Tone A Duration

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 10

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Sequence 3 Tone A Delay (sec)

Tag:SEQUENCE:S3 Tone A Delay

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 10

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Sequence 3 Tone B Duration (sec)

Tag:SEQUENCE:S3 Tone B Duration

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 10

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Sequence 3 Tone B Delay (sec)

Tag:SEQUENCE:S3 Tone B Delay

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 10

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Sequence 4 Tone A Duration (sec)

Tag:SEQUENCE:S4 Tone A Duration

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 10


Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Sequence 4 Tone A Delay (sec)

Tag:SEQUENCE:S4 Tone A Delay

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 46 OF 107	

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 10

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Sequence 4 Tone B Duration (sec)

Tag:SEQUENCE:S4 Tone B Duration

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 10

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Sequence 4 Tone B Delay (sec)

Tag:SEQUENCE:S4 Tone B Delay

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 10

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Tone A Frequency (Hz)

Tag:SEQUENCE:Tone A Frequency

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 20000

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Tone B Frequency (Hz)

Tag:SEQUENCE:Tone B Frequency

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 20000

Availability:

Menu:SEQUENCE

Typical Completion Time:100 ms

Name:Code Sequence

Tag:GENSEQ:Code Sequence

Commands:GET, SET

Data Type:STRING

Format:(GENSEQCode)

char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, E, F, G, H, I, J


Availability:

Menu:GENSEQ

Typical Completion Time:100 ms

Name>Select Tone Standard

Tag:GENSEQ:Standard

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 47 OF 107	

Commands:GET, SET
 Data Type:LIST
 List Values: None, CCIR1, CCIR2, PCCIR, CCITT, EEA, EIA, Euro, NATEL, MODAT, ZVEI1, ZVEI2, ZVEI3, PZVEI, DZVEI, PDZVEI
 Availability:
 Menu:GENSEQ
 Typical Completion Time:500 ms


Name:Synth Mode
 Tag:GENSEQ:Synth Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous, Burst [AUDIO:Format=A/B Sequence or AUDIO:Format=5/6 Tone or AUDIO:Format=POCSAG or AUDIO:Format=General Sequence], Disconnect Tone [AUDIO:Format=DPL or AUDIO:Format=DPL Invert]
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:GENSEQ
 Typical Completion Time:500 ms

Name:Select Symbol to Edit
 Tag:GENSEQ:Select Tone
 Commands:GET, SET
 Data Type:LIST
 List Values: 0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, E, F, G, H, I, J
 Availability:
 Menu:GENSEQ
 Typical Completion Time:100 ms

Name:Tone Frequency(Hz)
 Tag:GENSEQ>Edit Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 20000
 Availability:
 Menu:GENSEQ
 Typical Completion Time:100 ms

Name:Tone Duration(sec)
 Tag:GENSEQ>Edit Duration
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 0
 Availability:
 Menu:GENSEQ
 Typical Completion Time:100 ms

Name:Post-Tone Delay(sec)
 Tag:GENSEQ>Edit Delay
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 1
 Availability:
 Menu:GENSEQ
 Typical Completion Time:100 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 48 OF 107	

Name:Save Sequence Definition
 Tag:GENSEQ:Save
 Commands:GET, SET
 Data Type:STRING
 char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, E, F, G, H, I, J, K, L, M,
 N, O, P, Q, R, S, T, U, V, W, X, Y, Z, , ., _, (,)
 Availability:
 Menu:GENSEQ
 Typical Completion Time:2000 ms


Name:Load Sequence Definition
 Tag:GENSEQ:Load
 Commands:GET, SET
 Data Type:LIST
 List Values:
 Availability:
 Menu:GENSEQ
 Typical Completion Time:2000 ms

Name:Sync to Code Entry
 Tag:GENSEQ:Sync Sequences
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: No, Yes
 Availability:
 Menu:GENSEQ
 Typical Completion Time:100 ms

Name:Duration Sequence
 Tag:GENSEQ:Dur Sequence
 Commands:GET, SET
 Data Type:STRING
 Format:(GENSEQCode)
 char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, E, F, G, H, I, J
 Availability:
 Menu:GENSEQ
 Typical Completion Time:100 ms

Name:Delay Sequence
 Tag:GENSEQ:Delay Sequence
 Commands:GET, SET
 Data Type:STRING
 Format:(GENSEQCode)
 char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, E, F, G, H, I, J
 Availability:
 Menu:GENSEQ
 Typical Completion Time:100 ms

Name:Spectrum Analyzer
 Tag:INSTRUMENTS:SPEC_AN
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Menu:INSTRUMENTS

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 49 OF 107	

Typical Completion Time:2000 ms

Name:Modulation Scope
 Tag:INSTRUMENTS:MOD_SCOPE
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Menu:INSTRUMENTS
 Typical Completion Time:2000 ms

Name:Oscilloscope
 Tag:INSTRUMENTS:O_SCOPE
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Menu:INSTRUMENTS
 Typical Completion Time:2000 ms


Name:Dual Display
 Tag:INSTRUMENTS:DUAL_SCOPE
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Option:R8-ESA
 Menu:INSTRUMENTS
 Typical Completion Time:2000 ms

Name:Tracking Generator
 Tag:INSTRUMENTS:TRACK_GEN
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Option:R8-TG
 Menu:INSTRUMENTS
 Typical Completion Time:5000 ms

Name:Presets
 Tag:TEST:PRESETS
 Commands:GO
 Data Type:SUBMENU
 Typical Completion Time:2000 ms

Name:Test Mode
 Tag:TEST:Test Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Standard, DMR [Option=R8-DMR], PROJECT 25 [Option=R8-P25], P25 Trunk [Option=R8-P25TRNK], NXDN [Option=R8-NXDN], NXDN Trunk [Option=R8-NXDNTYPC], TETRA Base Station [Option=R8-TETRA_BSM], TETRA DMO [Option=R8-TETRA_DMO], TETRA TMO [Option=R8-TETRA_TMO], DPMR [Option=R8-DPMR], P25 II [Option=R8-P25_II], PTC-ITCR [Option=R8-PTC_ITCR], PTC-ACSES [Option=R8-PTC_ACSES]
 Typical Completion Time:5000 ms

Name:AutoScript

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 50 OF 107	

Tag:TEST:AUTOSCRIP
 Commands:GO
 Data Type:SUBMENU
 Typical Completion Time:0 ms

Name:System Settings
 Tag:SETTINGS:SETUP
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Menu:SETTINGS
 Typical Completion Time:2000 ms

Name:Battery Status
 Tag:SETTINGS:BATTERY
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Menu:SETTINGS
 Typical Completion Time:2000 ms


Name:Acknowledge Message
 Tag:SETTINGS:ACK_MESSAGE
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Menu:SETTINGS
 Typical Completion Time:0 ms

Name>About
 Tag:SETTINGS:ABOUT
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Menu:SETTINGS
 Typical Completion Time:2000 ms

Name:Options
 Tag:SETTINGS:OPTIONS
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Menu:SETTINGS
 Typical Completion Time:2000 ms

Name:PLL Lock Status
 Tag:MONITOR:PLL Status
 Commands:GET
 Data Type:INTEGER
 Typical Completion Time:0 ms

Name:High Power Attenuator Temp
 Tag:MONITOR:HP Attenuator Temp
 Commands:GET
 Data Type:FLOAT

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 51 OF 107	

Range: 0 to 100
 Typical Completion Time:0 ms

Name:Receive Power Meter Temp
 Tag:MONITOR:RX Power Meter Temp
 Commands:GET
 Data Type:FLOAT
 Range: 0 to 100
 Typical Completion Time:0 ms

Name:Generate Power Meter Temp
 Tag:MONITOR:Gen Power Meter Temp
 Commands:GET
 Data Type:FLOAT
 Range: 0 to 100
 Typical Completion Time:0 ms


Name:Frequency Error
 Tag:MONITOR:Frequency Error
 Commands:GET
 Data Type:FLOAT
 Typical Completion Time:0 ms

Name:Input Level
 Tag:MONITOR:Input Level
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:0 ms

Name:Deviation
 Tag:MONITOR:Deviation+
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:0 ms

Name:Deviation
 Tag:MONITOR:Deviation-
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Typical Completion Time:0 ms

Name:Center Frequency
 Tag:SPEC_AN:Monitor Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Monitor, Duplex

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 52 OF 107	

Menu:SPEC_AN
 Typical Completion Time:5000 ms


Name:Span
 Tag:SPEC_AN:Span
 Commands:GET, SET
 Data Type:FLOAT
 Range: 9751 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:5000 ms

Name:Start Frequency
 Tag:SPEC_AN:Start Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:5000 ms

Name:Stop Frequency
 Tag:SPEC_AN:Stop Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:5000 ms

Name:Resolution Bandwidth
 Tag:SPEC_AN:Resolution Bandwidth
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:0 ms

Name:Reference Level (dBm)
 Tag:SPEC_AN:Reference Level
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 90
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:100 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 53 OF 107	

Name:Vertical Scale
 Tag:SPEC_AN:Vertical Scale
 Commands:GET, SET
 Data Type:LIST
 List Values: 10 dB/div, 5 dB/div, 2 dB/div, 1 dB/div
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:100 ms


Name:Display Mode
 Tag:SPEC_AN:Display Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Normal, Freeze, Max Hold, Average
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:100 ms

Name:Trace Math
 Tag:SPEC_AN:Trace Math
 Commands:GET, SET
 Data Type:LIST
 List Values: None, Spec-Ref (log),
 Spec-Ref
 (lin), Spec+Ref (lin)
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:100 ms

Name:Set Reference Trace
 Tag:SPEC_AN:Set Reference Trace
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:100 ms

Name:Detector
 Tag:SPEC_AN:Detector
 Commands:GET, SET
 Data Type:LIST
 List Values: Power, Peak, Sample, Mean, Valley
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:SPEC_AN
 Typical Completion Time:200 ms

Name:Find Peak
 Tag:SPEC_AN:Find Peak
 Commands:DO
 Data Type:FUNCTION

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 54 OF 107	

Availability:

Operating Mode:Monitor, Duplex
 Menu:SPEC_AN

Typical Completion Time:100 ms

Name:Center Peak

Tag:SPEC_AN:Center Peak

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Monitor, Duplex
 Menu:SPEC_AN

Typical Completion Time:5000 ms

Name:OBW

Tag:SPEC_AN:OBW

Commands:GET, SET

Data Type:BOOLEAN

List Values: Off, On

Availability:

Operating Mode:Monitor, Duplex
 Option:R8-ESA
 Menu:SPEC_AN

Typical Completion Time:100 ms

Name:OBW %

Tag:SPEC_AN:OBW %

Commands:GET, SET

Data Type:INTEGER

Range: 70 to 99

Availability:

Operating Mode:Monitor, Duplex
 Option:R8-ESA
 Menu:SPEC_AN

Typical Completion Time:100 ms

Name>Select Instrument

Tag:DUAL_SCOPE:Subzone

Commands:GET, SET

Data Type:LIST

List Values: Spectrum Analyzer, Modulation Scope

Availability:

Menu:DUAL_SCOPE

Typical Completion Time:100 ms

Name:Span

Tag:DUAL_SCOPE:Span

Commands:GET, SET

Data Type:FLOAT


Range: 9751 Hz to 1000000000 Hz

Units: Hz, kHz, MHz, GHz

Availability:

Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer

Typical Completion Time:5000 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 55 OF 107	

Name:Start Frequency
 Tag:DUAL_SCOPE:Start Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:5000 ms


Name:Stop Frequency
 Tag:DUAL_SCOPE:Stop Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:5000 ms

Name:Resolution Bandwidth
 Tag:DUAL_SCOPE:Resolution Bandwidth
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:0 ms

Name:Reference Level (dBm)
 Tag:DUAL_SCOPE:Reference Level
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 90
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:100 ms

Name:Vertical Scale
 Tag:DUAL_SCOPE:Vertical Scale
 Commands:GET, SET
 Data Type:LIST
 List Values: 10 dB/div, 5 dB/div, 2 dB/div, 1 dB/div
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:100 ms

Name:Display Mode
 Tag:DUAL_SCOPE:Display Mode
 Commands:GET, SET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 56 OF 107	

Data Type:LIST
 List Values: Normal, Freeze, Max Hold, Average
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:100 ms


Name:Trace Math
 Tag:DUAL_SCOPE:Trace Math
 Commands:GET, SET
 Data Type:LIST
 List Values: None, Spec-Ref (log),
 Spec-Ref
 (lin), Spec+Ref (lin)
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:100 ms

Name:Set Reference Trace
 Tag:DUAL_SCOPE:Set Reference Trace
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:100 ms

Name:Detector
 Tag:DUAL_SCOPE:Detector
 Commands:GET, SET
 Data Type:LIST
 List Values: Power, Peak, Sample, Mean, Valley
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:200 ms

Name:Find Peak
 Tag:DUAL_SCOPE:Find Peak
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:100 ms

Name:Center Peak
 Tag:DUAL_SCOPE:Center Peak
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DUAL_SCOPE:Subzone=Spectrum Analyzer
 Typical Completion Time:5000 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 57 OF 107	

Name:Vertical Scale
 Tag:DUAL_SCOPE:AM Vertical Scale
 Commands:GET, SET
 Data Type:LIST
 List Values: 1%, 2%, 5%, 10%, 20%, 50%
 Availability:
 Menu:DUAL_SCOPE:Subzone=Modulation Scope
 Typical Completion Time:100 ms


Name:Vertical Scale
 Tag:DUAL_SCOPE:FM Vertical Scale
 Commands:GET, SET
 Data Type:LIST
 List Values: 100 Hz, 200 Hz, 500 Hz, 1 kHz, 2 kHz, 5 kHz, 10 kHz, 20 kHz, 50 kHz
 Availability:
 Menu:DUAL_SCOPE:Subzone=Modulation Scope
 Typical Completion Time:100 ms

Name:Horizontal Scale
 Tag:DUAL_SCOPE:Horizontal Scale
 Commands:GET, SET
 Data Type:LIST
 List Values: 20 us, 50 us, 100 us, 200 us, 500 us, 1 ms, 2 ms, 5 ms, 10 ms, 20 ms, 50 ms, 100 ms, 200 ms, 500 ms, 1 s
 Availability:
 Menu:DUAL_SCOPE:Subzone=Modulation Scope
 Typical Completion Time:100 ms

Name:Trigger Mode
 Tag:DUAL_SCOPE:Trigger
 Commands:GET, SET
 Data Type:LIST
 List Values: Auto, Normal, Single
 Availability:
 Menu:DUAL_SCOPE:Subzone=Modulation Scope
 Typical Completion Time:100 ms

Name:Trigger Level
 Tag:DUAL_SCOPE:Trigger Level
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 200000
 Availability:
 Menu:DUAL_SCOPE:Subzone=Modulation Scope
 Typical Completion Time:100 ms

Name:Trigger Level (%)
 Tag:DUAL_SCOPE:AM Trigger Level
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 99
 Availability:
 Menu:DUAL_SCOPE:Subzone=Modulation Scope

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 58 OF 107	

Typical Completion Time:100 ms

Name:Trigger Edge
 Tag:DUAL_SCOPE:Trigger Edge
 Commands:GET, SET
 Data Type:LIST
 List Values: Rising, Falling, Either
 Availability:
 Menu:DUAL_SCOPE:Subzone=Modulation Scope
 Typical Completion Time:100 ms


Name:Scope Mode
 Tag:DUAL_SCOPE:Mod Scope Select
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Monitor, Generate
 Availability:
 Operating Mode:Duplex
 Menu:DUAL_SCOPE
 Typical Completion Time:100 ms

Name:Center Frequency
 Tag:TRACK_GEN:Generate Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:5000 ms

Name:Span
 Tag:TRACK_GEN:Span
 Commands:GET, SET
 Data Type:FLOAT
 Range: 1 Hz to 50000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:5000 ms

Name:Start Frequency
 Tag:TRACK_GEN:Start Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 3000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:5000 ms

Name:Stop Frequency

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 59 OF 107	

Tag:TRACK_GEN:Stop Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 259751 Hz to 3000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:5000 ms


Name:Reference Level (dBm)
 Tag:TRACK_GEN:Reference Level
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 60
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:100 ms

Name:Vertical Scale
 Tag:TRACK_GEN:Vertical Scale
 Commands:GET, SET
 Data Type:LIST
 List Values: 15 dB/div, 10 dB/div, 5 dB/div, 2 dB/div, 1 dB/div
 Availability:
 Operating Mode:Track Gen
 Option:R8-ESA
 Menu:TRACK_GEN
 Typical Completion Time:100 ms

Name:# of Points
 Tag:TRACK_GEN:Number of Points
 Commands:GET, SET
 Data Type:INTEGER
 Range: 100 to 600
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:4000 ms

Name:RBW
 Tag:TRACK_GEN:RBW
 Commands:GET, SET
 Data Type:LIST
 List Values: Wide, Medium, Narrow
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:4000 ms

Name:Display Mode
 Tag:TRACK_GEN:Display Mode
 Commands:GET, SET
 Data Type:LIST

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 60 OF 107	

List Values: Normal, Freeze, Max Hold, Average
 Availability:

Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:100 ms


Name:Marker Mode
 Tag:TRACK_GEN:SA Markers
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Absolute, Delta
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:100 ms

Name:Marker Type
 Tag:TRACK_GEN:Marker Type
 Commands:GET, SET
 Data Type:LIST
 List Values: Point Cross, Vertical Bar, Horizontal Bar, Full Cross
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:100 ms

Name:Toggle Marker
 Tag:TRACK_GEN:Toggle Marker
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:100 ms

Name>Select Marker
 Tag:TRACK_GEN>Select Marker
 Commands:GET, SET
 Data Type:LIST
 List Values: 1, 2, 3, 4
 Availability:
 Operating Mode:Track Gen
 Option:R8-ESA
 Menu:TRACK_GEN
 Typical Completion Time:100 ms

Name:Set Marker Frequency
 Tag:TRACK_GEN:Marker Frequency
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 61 OF 107	

Typical Completion Time:100 ms

Name:Find Peak
 Tag:TRACK_GEN:Find Peak
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:100 ms


Name:Find Valley
 Tag:TRACK_GEN:Find Valley
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:100 ms

Name:Center Marker
 Tag:TRACK_GEN:Center Marker
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:5000 ms

Name:Output Level (dBm)
 Tag:TRACK_GEN:Output Level
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 5
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:500 ms

Name:Attenuation
 Tag:TRACK_GEN:Attenuation
 Commands:GET, SET
 Data Type:LIST
 List Values: 0 dB, 2 dB, 4 dB, 6 dB, 8 dB, 10 dB, 12 dB, 14 dB, 16 dB, 18 dB,
 20 dB, 22 dB, 24 dB, 26 dB, 28 dB, 30 dB, 32 dB, 34 dB, 36 dB, 38 dB, 40 dB,
 42 dB, 44 dB, 46 dB, 48 dB, 50 dB, 52 dB, 54 dB, 56 dB, 58 dB, 60 dB, 62 dB
 Availability:
 Operating Mode:Track Gen
 Menu:TRACK_GEN
 Typical Completion Time:500 ms

Name:Pre-Amplifier
 Tag:TRACK_GEN:PreAmp On
 Commands:GET, SET
 Data Type:BOOLEAN

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 62 OF 107	

List Values: Off, On

Availability:

Operating Mode:Track Gen

Menu:TRACK_GEN

Typical Completion Time:500 ms

Name:Gen Port

Tag:TRACK_GEN:Generate Port

Commands:GET, SET

Data Type:BOOLEAN

List Values: RF In/Out, Gen Out

Availability:

Operating Mode:Track Gen

Menu:TRACK_GEN

Typical Completion Time:500 ms

Name:Monitor Port

Tag:TRACK_GEN:Monitor Port

Commands:GET, SET

Data Type:BOOLEAN

List Values: RF In/Out, Antenna

Availability:

Operating Mode:Track Gen

Menu:TRACK_GEN

Typical Completion Time:500 ms

Name:Normalize

Tag:TRACK_GEN:Normalize

Commands:GET, SET

Data Type:BOOLEAN

List Values: Off, On

Availability:

Operating Mode:Track Gen

Menu:TRACK_GEN

Typical Completion Time:500 ms

Name:Update Trace

Tag:TRACK_GEN:Trace Request

Commands:

Data Type:BOOLEAN

List Values: F, T

Availability:

Operating Mode:Track Gen

Menu:TRACK_GEN

Typical Completion Time:100 ms

Name:

Tag:TRACK_GEN:Trace

Commands:GET


Data Type:ARRAY

Availability:

Operating Mode:Track Gen

Menu:TRACK_GEN

Typical Completion Time:100 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 63 OF 107	

Name: Coupling
 Tag: O_SCOPE: Coupling
 Commands: GET, SET
 Data Type: BOOLEAN
 List Values: DC, AC
 Availability:
 Menu: O_SCOPE
 Typical Completion Time: 500 ms


Name: Horizontal Scale
 Tag: O_SCOPE: Ext Horizontal Scale
 Commands: GET, SET
 Data Type: LIST
 List Values: 20 us (Max 50 kHz In), 50 us (Max 20 kHz In), 100 us (Max 10 kHz In), 200 us (Max 5 kHz In), 500 us (Max 2 kHz In), 1 ms (Max 1 kHz In), 2 ms (Max 500 Hz In), 5 ms (Max 200 Hz In), 10 ms (Max 100 Hz In), 20 ms (Max 50 Hz In), 50 ms (Max 20 Hz In), 100 ms (Max 10 Hz In), 200 ms (Max 5 Hz In), 500 ms (Max 2 Hz In), 1 s (Max 1 Hz In)
 Availability:
 Menu: O_SCOPE
 Typical Completion Time: 500 ms

Name: Vertical Scale
 Tag: O_SCOPE: Ext Vertical Scale
 Commands: GET, SET
 Data Type: LIST
 List Values: 50 mV, 100 mV, 200 mV, 500 mV, 1 V, 2 V, 5 V, 10 V, 15 V, 20 V, 25 V
 Availability:
 Menu: O_SCOPE
 Typical Completion Time: 500 ms

Name: Trigger Mode
 Tag: O_SCOPE: Ext Trigger
 Commands: GET, SET
 Data Type: LIST
 List Values: Auto, Normal, Single, Freeze
 Availability:
 Menu: O_SCOPE
 Typical Completion Time: 500 ms

Name: Trigger Level
 Tag: O_SCOPE: Ext Trigger Level
 Commands: GET, SET
 Data Type: FLOAT
 Range: 0 to 100
 Availability:
 Menu: O_SCOPE
 Typical Completion Time: 500 ms

Name: Trigger Position
 Tag: O_SCOPE: Ext Trigger Position
 Commands: GET, SET
 Data Type: LIST
 List Values: 10%, 50%, 90%

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 64 OF 107	

Availability:

Menu:O_SCOPE

Typical Completion Time:500 ms

Name:Trigger Edge

Tag:O_SCOPE:Ext Trigger Edge

Commands:GET, SET

Data Type:LIST

List Values: Rising, Falling, Either

Availability:

Menu:O_SCOPE

Typical Completion Time:500 ms

Name:Vertical Scale

Tag:MOD_SCOPE:AM Vertical Scale

Commands:GET, SET

Data Type:LIST

List Values: 1%, 2%, 5%, 10%, 20%, 50%

Availability:

Menu:MOD_SCOPE

Typical Completion Time:100 ms

Name:Vertical Scale

Tag:MOD_SCOPE:FM Vertical Scale

Commands:GET, SET

Data Type:LIST

List Values: 100 Hz, 200 Hz, 500 Hz, 1 kHz, 2 kHz, 5 kHz, 10 kHz, 20 kHz, 50 kHz

Availability:

Menu:MOD_SCOPE

Typical Completion Time:100 ms

Name:Horizontal Scale

Tag:MOD_SCOPE:Horizontal Scale

Commands:GET, SET

Data Type:LIST

List Values: 20 us, 50 us, 100 us, 200 us, 500 us, 1 ms, 2 ms, 5 ms, 10 ms, 20 ms, 50 ms, 100 ms, 200 ms, 500 ms, 1 s

Availability:

Menu:MOD_SCOPE

Typical Completion Time:100 ms

Name:Trigger Mode

Tag:MOD_SCOPE:Trigger

Commands:GET, SET

Data Type:LIST

List Values: Auto, Normal, Single

Availability:

Menu:MOD_SCOPE


Typical Completion Time:100 ms

Name:Trigger Level

Tag:MOD_SCOPE:Trigger Level

Commands:GET, SET

Data Type:INTEGER

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 65 OF 107	

Range: 0 to 200000

Availability:

Menu:MOD_SCOPE

Typical Completion Time:100 ms

Name:Trigger Level (%)

Tag:MOD_SCOPE:AM Trigger Level

Commands:GET, SET

Data Type:INTEGER

Range: 0 to 99

Availability:

Menu:MOD_SCOPE

Typical Completion Time:100 ms

Name:Trigger Edge

Tag:MOD_SCOPE:Trigger Edge

Commands:GET, SET

Data Type:LIST

List Values: Rising, Falling, Either

Availability:

Menu:MOD_SCOPE

Typical Completion Time:100 ms

Name:Scope Mode

Tag:MOD_SCOPE:Mod Scope Select

Commands:GET, SET

Data Type:BOOLEAN

List Values: Monitor, Generate

Availability:

Operating Mode:Duplex

Menu:MOD_SCOPE

Typical Completion Time:100 ms

Name:System Version

Tag:ABOUT:SystemVersion

Commands:GET

Data Type:STRING

Availability:

Menu:ABOUT

Typical Completion Time:0 ms

Name:Application Version

Tag:ABOUT:AppVersion

Commands:GET

Data Type:STRING

Availability:

Menu:ABOUT

Typical Completion Time:0 ms

Name:R8000 Library Version


Tag:ABOUT:DllVersion

Commands:GET

Data Type:STRING

Availability:

Menu:ABOUT

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 66 OF 107	

Typical Completion Time:0 ms

Name:Signal Service Provider Version

Tag:ABOUT:SSP_Version

Commands:GET

Data Type:STRING

Availability:

Menu:ABOUT

Typical Completion Time:0 ms

Name:Audio Library Version

Tag:ABOUT:AudioVersion

Commands:GET

Data Type:STRING

Availability:

Menu:ABOUT

Typical Completion Time:0 ms

Name:Operating System Version

Tag:ABOUT:OSVersion

Commands:GET

Data Type:STRING

Availability:

Menu:ABOUT

Typical Completion Time:0 ms

Name:BIOS Version

Tag:ABOUT:BIOSVersion

Commands:GET

Data Type:STRING

Availability:

Menu:ABOUT

Typical Completion Time:0 ms

Name:Main Board Revision

Tag:ABOUT:MainPCBA

Commands:GET

Data Type:STRING

Availability:

Menu:ABOUT

Typical Completion Time:0 ms

Name:RF Board Revision

Tag:ABOUT:RfPCBA

Commands:GET

Data Type:STRING

Availability:

Menu:ABOUT

Typical Completion Time:0 ms


Name:Control FPGA Version

Tag:ABOUT:ControlFPGA

Commands:GET

Data Type:STRING

Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 67 OF 107	

Menu:ABOUT
 Typical Completion Time:0 ms

Name:
 Tag:ABOUT:TxFPGA
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:ABOUT
 Typical Completion Time:0 ms

Name:RX FPGA Version
 Tag:ABOUT:RxFPGA
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:ABOUT
 Typical Completion Time:0 ms


Name:Comm FPGA Version
 Tag:ABOUT:PCIEFPGA
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:ABOUT
 Typical Completion Time:0 ms

Name:XTX BC Version
 Tag:ABOUT:XTX_BC
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:ABOUT
 Typical Completion Time:0 ms

Name:XTX Product Revision
 Tag:ABOUT:XTX_Product
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:ABOUT
 Typical Completion Time:0 ms

Name:XTX Serial Number
 Tag:ABOUT:XTX_Serial
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:ABOUT
 Typical Completion Time:0 ms

Name:Input Decoding
 Tag:SETUP:Input Decoding
 Commands:GET, SET
 Data Type:BOOLEAN

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 68 OF 107	

List Values: Internal, External

Availability:

Menu:SETUP

Typical Completion Time:100 ms

Name:Input Impedance

Tag:SETUP:Input Impedance

Commands:GET, SET

Data Type:BOOLEAN

List Values: 1 MegOhm, 600 Ohm

Availability:

Menu:SETUP

Typical Completion Time:100 ms

Name:Reference Clock Mode

Tag:SETUP:Ref Clock Mode

Commands:GET, SET

Data Type:BOOLEAN

List Values: Output, Input

Availability:

Menu:SETUP

Typical Completion Time:500 ms

Name:Analog Measurement Averaging

Tag:SETUP:Analog Msr Averaging

Commands:GET, SET

Data Type:BOOLEAN

List Values: Off, On

Availability:

Menu:SETUP

Typical Completion Time:100 ms

Name:Analog Averaging Samples

Tag:SETUP:Analog Msr Avg Samples

Commands:GET, SET

Data Type:INTEGER

Range: 2 to 100

Availability:

Menu:SETUP

Typical Completion Time:100 ms

Name:Digital Measurement Averaging

Tag:SETUP:Digital Msr Averaging

Commands:GET, SET

Data Type:BOOLEAN

List Values: Off, On

Availability:

Menu:SETUP

Typical Completion Time:100 ms


Name:Digital Averaging Samples

Tag:SETUP:Digital Msr Avg Samples

Commands:GET, SET

Data Type:INTEGER

Range: 2 to 100

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 69 OF 107	

Availability:

Menu:SETUP
 Typical Completion Time:100 ms

Name:Automatic Attenuation

Tag:SETUP:Auto Attn
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Off, On

Availability:

Menu:SETUP
 Typical Completion Time:100 ms

Name:Auto Attn Minimum

Tag:SETUP:Auto Attn Min
 Commands:GET, SET
 Data Type:LIST
 List Values: 0 dB, 2 dB, 4 dB, 6 dB, 8 dB, 10 dB, 12 dB, 14 dB, 16 dB, 18 dB, 20 dB, 22 dB, 24 dB, 26 dB, 28 dB, 30 dB, 32 dB, 34 dB

Availability:

Menu:SETUP
 Typical Completion Time:100 ms

Name:Auto Attn High Threshold

Tag:SETUP:Auto Attn Thd Hi
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 0

Availability:

Menu:SETUP
 Typical Completion Time:100 ms

Name:Auto Attn Low Threshold

Tag:SETUP:Auto Attn Thd Lo
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 0

Availability:

Menu:SETUP
 Typical Completion Time:100 ms

Name:Pre-Amplifier Auto Off


Tag:SETUP:PreAmp Auto Off
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Disabled, Enabled

Availability:

Menu:SETUP
 Typical Completion Time:100 ms

Name:RF Level Offset

Tag:SETUP:RF Level Offset
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Off, On

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 70 OF 107	

Availability:

Menu:SETUP

Typical Completion Time:100 ms

Name:RF In/Out Offset (dB)

Tag:SETUP:RF In/Out Offset

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 99

Availability:

Menu:SETUP

Typical Completion Time:500 ms

Name:RF Gen Out Offset (dB)

Tag:SETUP:RF Gen Out Offset

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 99

Availability:

Menu:SETUP

Typical Completion Time:500 ms

Name:Antenna Offset (dB)

Tag:SETUP:Antenna Offset

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 99

Availability:

Menu:SETUP

Typical Completion Time:500 ms

Name:Pre/De-emphasis

Tag:SETUP:Emphasis

Commands:GET, SET

Data Type:BOOLEAN

List Values: Off, On

Availability:

Menu:SETUP

Typical Completion Time:100 ms

Name:Meter In Filter

Tag:SETUP:Meter In Filter

Commands:GET, SET

Data Type:LIST

List Values: None, C-Msg, CCITT, De-emphasis

Availability:

Menu:SETUP

Typical Completion Time:100 ms

Name:Internal Audio Weighting


Tag:SETUP:Internal Audio Weight

Commands:GET, SET

Data Type:LIST

List Values: None, C-Msg, CCITT

Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 71 OF 107	

Menu:SETUP
 Typical Completion Time:100 ms

Name:Language
 Tag:SETUP:Language Select
 Commands:GET, SET
 Data Type:LIST
 List Values: English, Spanish
 Availability:

Menu:SETUP
 Typical Completion Time:6000 ms

Name:Date
 Tag:SETUP:NewDate
 Commands:GET, SET
 Data Type:STRING
 Format:(MM.DD.YYYY)
 char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, .
 Availability:

Menu:SETUP
 Typical Completion Time:100 ms

Name:Time
 Tag:SETUP:NewTime
 Commands:GET, SET
 Data Type:STRING
 Format:(HH:MM)
 char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, :
 Availability:

Menu:SETUP
 Typical Completion Time:100 ms

Name:Apply Date/Time Changes
 Tag:SETUP:ApplyDateTime
 Commands:DO
 Data Type:FUNCTION
 Availability:


Menu:SETUP
 Typical Completion Time:100 ms

Name:R8000 Legacy Mode
 Tag:SETUP:Legacy
 Commands:GET, SET
 Data Type:LIST
 List Values: Standard R8100, Legacy R8000
 Availability:

Menu:SETUP
 Typical Completion Time:500 ms

Name:Reset to Defaults
 Tag:SETUP:DefaultSetups
 Commands:DO
 Data Type:FUNCTION
 Availability:

Menu:SETUP

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 72 OF 107	

Typical Completion Time:100 ms

Name:Cable Sweep
 Tag:SETUP:Cable Sweep
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Off, On
 Availability:
 Menu:SETUP
 Typical Completion Time:100 ms

Name:Select Frequency to Edit
 Tag:SETUP:Select Frequency
 Commands:GET, SET
 Data Type:LIST
 List Values: 100, 1000
 Availability:
 Menu:SETUP
 Typical Completion Time:100 ms


Name:Select Attenuation to Edit
 Tag:SETUP:Select Attenuation
 Commands:GET, SET
 Data Type:ARRAY
 Availability:
 Menu:SETUP
 Typical Completion Time:100 ms

Name:
 Tag:BATTERY:SerialNumber
 Commands:GET
 Data Type:INTEGER
 Availability:
 Menu:BATTERY
 Typical Completion Time:0 ms

Name:
 Tag:BATTERY:TimeToEmpty
 Commands:GET
 Data Type:FLOAT
 Availability:
 Menu:BATTERY
 Typical Completion Time:0 ms

Name:
 Tag:BATTERY:TimeToFull
 Commands:GET
 Data Type:FLOAT
 Availability:
 Menu:BATTERY
 Typical Completion Time:0 ms

Name:
 Tag:BATTERY:Temperature
 Commands:GET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 73 OF 107	

Data Type:FLOAT

Availability:

Menu:BATTERY

Typical Completion Time:0 ms

Name:

Tag:BATTERY:CycleCount

Commands:GET

Data Type:INTEGER

Availability:

Menu:BATTERY

Typical Completion Time:0 ms

Name:

Tag:BATTERY:Charge

Commands:GET

Data Type:FLOAT

Availability:

Menu:BATTERY

Typical Completion Time:0 ms

Name:

Tag:BATTERY:Charging

Commands:GET

Data Type:BOOLEAN

List Values:

Availability:

Menu:BATTERY

Typical Completion Time:0 ms

Name:Save Configuration As

Tag:PRESETS:New

Commands:GET, SET

Data Type:STRING

char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, A, B, C, D, E, F, G, H, I, J, K, L, M,

N, O, P, Q, R, S, T, U, V, W, X, Y, Z, , ., _ , (,)

Availability:

Menu:PRESETS

Typical Completion Time:2000 ms

Name:Load Factory Configuration

Tag:PRESETS:Load Defaults

Commands:DO

Data Type:FUNCTION

Availability:

Menu:PRESETS

Typical Completion Time:15000 ms

Name:RF Level Offset

Tag:AUTOTUNE:RF Level Offset


Commands:GET, SET

Data Type:BOOLEAN

List Values: Off, On

Availability:

Menu:AUTOTUNE

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 74 OF 107	

Typical Completion Time:100 ms

Name:RF In/Out Offset (dB)
 Tag:AUTOTUNE:RF In/Out Offset
 Commands:GET, SET
 Data Type:FLOAT
 Range: 0 to 99
 Availability:
 Menu:AUTOTUNE
 Typical Completion Time:500 ms


Name:Brand
 Tag:DMR:Brand
 Commands:GET, SET
 Data Type:LIST
 List Values: MOTOTRBO™, Other
 Availability:
 Menu:DMR
 Typical Completion Time:100 ms

Name:Mon Sync Pattern
 Tag:DMR:SYNC Pattern
 Commands:GET, SET
 Data Type:LIST
 List Values: BS Sourced Voice, BS Sourced Data, MS Sourced Voice
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DMR
 Typical Completion Time:100 ms

Name:
 Tag:DMR:SYNC Count
 Commands:GET
 Data Type:INTEGER
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DMR
 Typical Completion Time:0 ms

Name:
 Tag:DMR:Source ID
 Commands:GET
 Data Type:INTEGER
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DMR
 Typical Completion Time:0 ms

Name:Color Code
 Tag:DMR:Monitor CC
 Commands:GET
 Data Type:STRING
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:DMR

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 75 OF 107	

Typical Completion Time:0 ms

Name:Copy CC to Generator

Tag:DMR:Copy CC to Generator

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Monitor, Duplex

Menu:DMR

Typical Completion Time:100 ms

Name:Color Code

Tag:DMR:Color Code

Commands:GET, SET

Data Type:INTEGER

Range: 0 to 15

Availability:

Operating Mode:Generate, Duplex

Menu:DMR

Typical Completion Time:100 ms

Name:Burst

Tag:DMR:Burst

Commands:GET, SET

Data Type:LIST

List Values: A, B, C, D, E, F

Availability:

Operating Mode:Monitor, Duplex

Menu:DMR

Typical Completion Time:100 ms

Name:BER Test

Tag:DMR:BER Test

Commands:GET, SET

Data Type:LIST

List Values: Stop, Start

Availability:

Operating Mode:Monitor

Menu:DMR

Typical Completion Time:500 ms

Name:Modulation Mode

Tag:DMR:Gen Mod Mode

Commands:GET, SET

Data Type:LIST

List Values: Off, Continuous

Availability:

Operating Mode:Generate, Duplex

Menu:DMR


Typical Completion Time:500 ms

Name:Test Pattern

Tag:DMR:Test Pattern

Commands:GET, SET

Data Type:LIST

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 76 OF 107	

List Values: 1031 Hz Tone, Calibration (0.153 1%), 0.153, Silence, BS Idle
 Availability:

Operating Mode:Generate, Duplex
 Menu:DMR

Typical Completion Time:100 ms

Name:

Tag:DMR:Symbol Deviation

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor, Duplex
 Menu:DMR

Typical Completion Time:0 ms

Name:

Tag:DMR:FSK Error

Commands:GET

Data Type:FLOAT

Range: 0 to 100

Availability:

Operating Mode:Monitor, Duplex
 Menu:DMR

Typical Completion Time:0 ms

Name:

Tag:DMR:Magnitude Error

Commands:GET

Data Type:FLOAT

Range: 0 to 100

Availability:

Operating Mode:Monitor, Duplex
 Menu:DMR

Typical Completion Time:0 ms

Name:

Tag:DMR:BER Result

Commands:GET

Data Type:FLOAT

Range: 0 to 100

Availability:

Operating Mode:Monitor
 Menu:DMR

Typical Completion Time:0 ms

Name:DMR Library Version

Tag:DMR:Version

Commands:GET

Data Type:STRING


Availability:

Menu:DMR

Typical Completion Time:0 ms

Name:

Tag:P25:BER Result

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 77 OF 107	

Commands:GET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Menu:P25
 Typical Completion Time:0 ms

Name:
 Tag:P25:Symbol Deviation
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:0 ms


Name:
 Tag:P25:Symbol Rate Error
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:0 ms

Name:
 Tag:P25:EVM
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:0 ms

Name:
 Tag:P25:Modulation Fidelity
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:0 ms

Name:Mon Test Pattern
 Tag:P25:Mon Test Pattern
 Commands:GET, SET
 Data Type:LIST
 List Values: 1011 Hz Tone, Calibration (Tone 5%), Standard Tx (0.153/V.52),
 Silence, Modified 1011 Hz
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:100 ms

Name:Gen Test Pattern

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 78 OF 107	

Tag:P25:Gen Test Pattern

Commands:GET, SET

Data Type:LIST

List Values: 1011 Hz Tone, Calibration (Tone 5%), Standard Tx (0.153/V.52), Silence, Symbol Rate [Operating Mode=Generate], Low Deviation [Operating Mode=Generate], C4FM Mod Fidelity [Operating Mode=Generate]

Availability:

Operating Mode:Generate, Duplex

Menu:P25

Typical Completion Time:100 ms

Name:Generate Modulation Type

Tag:P25:Modulation Type

Commands:GET, SET

Data Type:LIST

List Values: FM [Test Mode=Standard], AM [Test Mode=Standard], USB [Test Mode=Standard and Option=R8-SSB], LSB [Test Mode=Standard and Option=R8-SSB], 4FSK [Test Mode=DMR or Test Mode=DPMR or Test Mode=NXDN], GMSK~ [Test Mode=PTC-ACSES], C4FM [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], LSM [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], WCQPSK [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], pi/4 DQPSK [Test Mode=PTC-ITCR or Test Mode=TETRA DMO or Test Mode=TETRA TMO or Test Mode=TETRA BST], HCPM [Test Mode=P25 II], HDQPSK [Test Mode=P25 II and Operating Mode=Monitor or Test Mode=P25 II and Operating Mode=Generate]

Availability:

Operating Mode:Generate, Duplex

Menu:P25

Typical Completion Time:100 ms

Name:Modulation Mode

Tag:P25:Gen Mod Mode

Commands:GET, SET

Data Type:LIST

List Values: Off, Continuous, Burst

Availability:

Operating Mode:Generate, Duplex

Menu:P25

Typical Completion Time:500 ms

Name:NAC (Hex)

Tag:P25:NAC

Commands:GET, SET

Data Type:STRING

Format:0x000

Availability:

Operating Mode:Generate, Duplex

Menu:P25

Typical Completion Time:100 ms

Name:Monitor Modulation Type


Tag:P25:Mon Mod Type

Commands:GET, SET

Data Type:LIST

List Values: C4FM, LSM, WCQPSK

Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 79 OF 107	

Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:100 ms

Name:Monitor NAC
 Tag:P25:Monitor NAC

Commands:
 Data Type:STRING
 Format:0x000

Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:100 ms

Name:Reset Symbol Rate Error

Tag:P25:Reset SRE

Commands:DO
 Data Type:FUNCTION

Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:100 ms

Name:BER Test

Tag:P25:BER Test

Commands:GET, SET

Data Type:LIST
 List Values: Stop, Start

Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:500 ms

Name:Eye Diagram Data

Tag:P25:Eye Data

Commands:GET

Data Type:ARRAY

Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25
 Typical Completion Time:100 ms

Name:Voice Frame Encoder

Tag:P25:P25_VFENCODE Table

Commands:GO

Data Type:SUBMENU


Availability:
 Operating Mode:Generate, Duplex
 Menu:P25
 Typical Completion Time:2000 ms

Name:Voice Frame Data

Tag:P25:Voice Frames

Commands:GET

Data Type:ARRAY

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 80 OF 107	

Availability:

Operating Mode:Monitor, Duplex
Menu:P25

Typical Completion Time:100 ms

Name:Copy NAC to Generator

Tag:P25:Copy NAC to Generator

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Monitor, Duplex
Menu:P25

Typical Completion Time:100 ms

Name:Project 25 Library Version

Tag:P25:Version

Commands:GET

Data Type:STRING

Availability:

Menu:P25

Typical Completion Time:0 ms

Name:NAC (Hex)

Tag:P25_VFENCODE:NAC

Commands:GET, SET

Data Type:STRING

Format:0x000

Availability:

Operating Mode:Generate, Duplex
Menu:P25_VFENCODE

Typical Completion Time:100 ms

Name:Key ID (Hex)

Tag:P25_VFENCODE:KID

Commands:GET, SET

Data Type:STRING

Format:0x0000

Availability:

Operating Mode:Generate, Duplex
Menu:P25_VFENCODE

Typical Completion Time:100 ms

Name:Algorithm ID (Hex)

Tag:P25_VFENCODE:ALGID

Commands:GET, SET

Data Type:STRING

Format:0x00

Availability:

Operating Mode:Generate, Duplex
Menu:P25_VFENCODE

Typical Completion Time:100 ms

Name:Status Symbols

Tag:P25_VFENCODE:SS

Commands:GET, SET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 81 OF 107	

Data Type:LIST
 List Values: 0 - Unknown Talkaround, 1 - Busy, 2 - Unknown In/Out, 3 - Idle
 Availability:

Operating Mode:Generate, Duplex
 Menu:P25_VFENCODE

Typical Completion Time:100 ms

Name:Low Speed Data (Hex)

Tag:P25_VFENCODE:LSD

Commands:GET, SET

Data Type:STRING

Format:0x00000000

Availability:

Operating Mode:Generate, Duplex
 Menu:P25_VFENCODE

Typical Completion Time:100 ms

Name:Talk Group ID (Hex)

Tag:P25_VFENCODE:Group Address

Commands:GET, SET

Data Type:STRING

Format:0x0000

Availability:

Operating Mode:Generate, Duplex
 Menu:P25_VFENCODE

Typical Completion Time:100 ms

Name:MFID (Hex)

Tag:P25_VFENCODE:MFID

Commands:GET, SET

Data Type:STRING

Format:0x00

Availability:

Operating Mode:Generate, Duplex
 Menu:P25_VFENCODE

Typical Completion Time:100 ms

Name:Raw (Hex)

Tag:P25_VFENCODE:Raw

Commands:GET, SET

Data Type:STRING

Format:0x00000000000000000000

Availability:

Operating Mode:Generate, Duplex
 Menu:P25_VFENCODE:Subzone=Raw

Typical Completion Time:100 ms

Name:Link Control Opcode

Tag:P25_VFENCODE:Subzone


Commands:GET, SET

Data Type:LIST

List Values: Raw, 0 - LC_GRP_V_CH_USR, 3 - LC_U2U_V_CH_USR

Availability:

Operating Mode:Generate, Duplex
 Menu:P25_VFENCODE

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 82 OF 107	

Typical Completion Time:100 ms

Name:SF - MFID Format

Tag:P25_VFENCODE:SF

Commands:GET, SET

Data Type:LIST

List Values: 0 - Explicit Format, 1 - Standard MFID

Availability:

Operating Mode:Generate, Duplex

Menu:P25_VFENCODE:Subzone=0 - LC_GRP_V_CH_USR, 3 - LC_U2U_V_CH_USR

Typical Completion Time:100 ms

Name:Service Options (Hex)

Tag:P25_VFENCODE:Service Options

Commands:GET, SET

Data Type:STRING

Format:0x00

Availability:

Operating Mode:Generate, Duplex

Menu:P25_VFENCODE:Subzone=0 - LC_GRP_V_CH_USR, 3 - LC_U2U_V_CH_USR

Typical Completion Time:100 ms

Name:S - Explicit Source ID

Tag:P25_VFENCODE:S

Commands:GET, SET

Data Type:LIST

List Values: 0 - Not Required, 1 - Required

Availability:

Operating Mode:Generate, Duplex

Menu:P25_VFENCODE:Subzone=0 - LC_GRP_V_CH_USR

Typical Completion Time:100 ms

Name:Target Address (Hex)

Tag:P25_VFENCODE:Target Address

Commands:GET, SET

Data Type:STRING

Format:0x000000

Availability:

Operating Mode:Generate, Duplex

Menu:P25_VFENCODE:Subzone=3 - LC_U2U_V_CH_USR

Typical Completion Time:100 ms

Name:Source Address (Hex)

Tag:P25_VFENCODE:Source Address

Commands:GET, SET

Data Type:STRING

Format:0x000000

Availability:

Operating Mode:Generate, Duplex


Menu:P25_VFENCODE:Subzone=0 - LC_GRP_V_CH_USR, 3 - LC_U2U_V_CH_USR

Typical Completion Time:100 ms

Name:Reset to Defaults

Tag:P25_VFENCODE:Reset

Commands:DO

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 83 OF 107	

Data Type:FUNCTION

Availability:

Operating Mode:Generate, Duplex

Menu:P25_VFENCODE

Typical Completion Time:200 ms

Name:Subzone

Tag:P25_TRUNK:Subzone

Commands:GET, SET

Data Type:LIST

List Values: Alert/Dispatch, BER

Availability:

Operating Mode:Duplex

Menu:P25_TRUNK

Typical Completion Time:100 ms

Name:Generate Modulation Type

Tag:P25_TRUNK:Modulation Type

Commands:GET, SET

Data Type:LIST

List Values: FM [Test Mode=Standard], AM [Test Mode=Standard], USB [Test Mode=Standard and Option=R8-SSB], LSB [Test Mode=Standard and Option=R8-SSB], 4FSK [Test Mode=DMR or Test Mode=DPMR or Test Mode=NXDN], GMSK~ [Test Mode=PTC-ACSES], C4FM [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], LSM [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], WCQPSK [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], pi/4 DQPSK [Test Mode=PTC-ITCR or Test Mode=TETRA DMO or Test Mode=TETRA TMO or Test Mode=TETRA BST], HCPM [Test Mode=P25 II], HDQPSK [Test Mode=P25 II and Operating Mode=Monitor or Test Mode=P25 II and Operating Mode=Generate]

Availability:

Operating Mode:Duplex

Menu:P25_TRUNK

Typical Completion Time:100 ms

Name:Modulation Mode

Tag:P25_TRUNK:Gen Mod Mode

Commands:GET, SET

Data Type:LIST

List Values: Off, Continuous

Availability:

Operating Mode:Duplex

Menu:P25_TRUNK:Subzone=BER

Typical Completion Time:500 ms

Name:NAC (Hex)

Tag:P25_TRUNK:NAC

Commands:GET, SET

Data Type:STRING

Format:0x000


Availability:

Operating Mode:Duplex

Menu:P25_TRUNK

Typical Completion Time:100 ms

Name:Voice Call

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 84 OF 107	

Tag:P25_TRUNK:Voice Call
 Commands:GET, SET
 Data Type:LIST
 List Values: Stop, Start
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms


Name:Send Call Alert
 Tag:P25_TRUNK:Call Alert
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:WACN ID (Hex)
 Tag:P25_TRUNK:WACN ID
 Commands:GET, SET
 Data Type:STRING
 Format:0x00000
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:SYSTEM ID (Hex)
 Tag:P25_TRUNK:SYSTEM ID
 Commands:GET, SET
 Data Type:STRING
 Format:0x000
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:WUID (Hex)
 Tag:P25_TRUNK:WUID
 Commands:GET, SET
 Data Type:STRING
 Format:0x000000
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:RFSS ID (Hex)
 Tag:P25_TRUNK:RFSS ID
 Commands:GET, SET
 Data Type:STRING
 Format:0x00
 Availability:
 Operating Mode:Duplex

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 85 OF 107	

Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:WGID (Hex)
 Tag:P25_TRUNK:WGID
 Commands:GET, SET
 Data Type:STRING
 Format:0x0000
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms


Name:SITE ID (Hex)
 Tag:P25_TRUNK:SITE ID
 Commands:GET, SET
 Data Type:STRING
 Format:0x00
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:Bandplan Table
 Tag:P25_TRUNK:BANDPLAN Table
 Commands:GO
 Data Type:SUBMENU
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:2000 ms

Name:Identifier Update
 Tag:P25_TRUNK:Iden Up
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: OFF, ON
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:Control Chnl TX Frequency
 Tag:P25_TRUNK:CCTx
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:Control Chnl RX Frequency
 Tag:P25_TRUNK:CCRx

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 86 OF 107	

Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms


Name:CCTx Channel
 Tag:P25_TRUNK:CCTx Chnl
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 4095
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:CCRx Channel
 Tag:P25_TRUNK:CCRx Chnl
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 4095
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:Voice Chnl TX Frequency
 Tag:P25_TRUNK:VCTx
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:Voice Chnl RX Frequency
 Tag:P25_TRUNK:VCRx
 Commands:GET, SET
 Data Type:FLOAT
 Range: 250000 Hz to 1000000000 Hz
 Units: Hz, kHz, MHz, GHz
 Availability:
 Operating Mode:Duplex
 Menu:P25_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:VCTx Channel
 Tag:P25_TRUNK:VCTx Chnl
 Commands:GET, SET
 Data Type:INTEGER

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 87 OF 107	

Range: 0 to 4095

Availability:

Operating Mode: Duplex

Menu: P25_TRUNK:Subzone=Alert/Dispatch

Typical Completion Time: 100 ms

Name: VCRx Channel

Tag: P25_TRUNK:VCRx Chnl

Commands: GET, SET

Data Type: INTEGER

Range: 0 to 4095

Availability:

Operating Mode: Duplex

Menu: P25_TRUNK:Subzone=Alert/Dispatch

Typical Completion Time: 100 ms

Name: Reset Symbol Rate Error

Tag: P25_TRUNK:Reset SRE

Commands: DO

Data Type: FUNCTION

Availability:

Operating Mode: Duplex

Menu: P25_TRUNK

Typical Completion Time: 100 ms

Name: BER Test

Tag: P25_TRUNK:BER Test

Commands: GET, SET

Data Type: LIST

List Values: Stop, Start

Availability:

Operating Mode: Duplex

Menu: P25_TRUNK

Typical Completion Time: 500 ms

Name: Test Pattern

Tag: P25_TRUNK:Test Pattern

Commands: GET, SET

Data Type: LIST

List Values: 1011 Hz Tone, Calibration (Tone 5%), Standard Tx (0.153/V.52), Silence

Availability:

Operating Mode: Duplex

Menu: P25_TRUNK:Subzone=BER

Typical Completion Time: 100 ms

Name: BS Mode

Tag: P25_TRUNK:P25_EXP

Commands: GET, SET

Data Type: LIST


List Values: Implicit, Explicit

Availability:

Operating Mode: Duplex

Option: R8-P25_EXP

Menu: P25_TRUNK:Subzone=Alert/Dispatch

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 88 OF 107	

Typical Completion Time:100 ms

Name:Band

Tag:BANDPLAN:Band

Commands:GET, SET

Data Type:LIST

List Values: 800 MHz, 700 MHz, UHF/VHF

Availability:

Operating Mode:Duplex

Menu:BANDPLAN

Typical Completion Time:100 ms

Name:Set Band Plan to Defaults

Tag:BANDPLAN:Band Defaults

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Duplex

Menu:BANDPLAN

Typical Completion Time:200 ms

Name:Bandwidth

Tag:BANDPLAN:Bandwidth

Commands:GET, SET

Data Type:LIST

List Values: 6.25 kHz, 12.5 kHz

Availability:

Operating Mode:Duplex

Menu:BANDPLAN

Typical Completion Time:100 ms

Name:Base Frequency

Tag:BANDPLAN:Base Frequency

Commands:GET, SET

Data Type:FLOAT

Range: 250000 Hz to 1000000000 Hz

Units: Hz, kHz, MHz, GHz

Availability:

Operating Mode:Duplex

Menu:BANDPLAN

Typical Completion Time:100 ms

Name:Channel Spacing (kHz)

Tag:BANDPLAN:Chnl Spacing

Commands:GET, SET

Data Type:FLOAT

Range: 0 to 512

Availability:

Operating Mode:Duplex


Menu:BANDPLAN

Typical Completion Time:100 ms

Name:Transmit Offset (MHz)

Tag:BANDPLAN:TX Offset

Commands:GET, SET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 89 OF 107	

Data Type:FLOAT

Availability:

Operating Mode:Duplex

Menu:BANDPLAN

Typical Completion Time:100 ms

Name:Channel Identifier

Tag:BANDPLAN:Channel Id

Commands:GET, SET

Data Type:INTEGER

Range: 1 to 16

Availability:

Operating Mode:Duplex

Menu:BANDPLAN

Typical Completion Time:100 ms

Name:

Tag:NXDN:BER Result

Commands:GET

Data Type:FLOAT

Range: 0 to 100

Availability:

Operating Mode:Monitor

Menu:NXDN

Typical Completion Time:0 ms

Name:

Tag:NXDN:Symbol Deviation

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor

Menu:NXDN

Typical Completion Time:0 ms

Name:

Tag:NXDN:Modulation Fidelity

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor

Menu:NXDN

Typical Completion Time:0 ms

Name:Bit Rate (bps)

Tag:NXDN:Bit Rate

Commands:GET, SET

Data Type:BOOLEAN

List Values: 4800, 9600


Availability:

Operating Mode:Monitor, Generate

Menu:NXDN

Typical Completion Time:100 ms

Name:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 90 OF 107	

Tag:NXDN:Monitor RAN

Commands:GET

Data Type:STRING

Availability:

Menu:NXDN

Typical Completion Time:0 ms

Name:Copy RAN to Generator

Tag:NXDN:Copy RAN to Generator

Commands:DO

Data Type:FUNCTION

Availability:

Operating Mode:Monitor

Menu:NXDN

Typical Completion Time:100 ms

Name:RAN

Tag:NXDN:Generate RAN

Commands:GET, SET

Data Type:INTEGER

Range: 0 to 63

Availability:

Operating Mode:Generate

Menu:NXDN

Typical Completion Time:100 ms

Name:Mon Test Pattern

Tag:NXDN:Mon Test Pattern

Commands:GET, SET

Data Type:LIST

List Values: 1031 Hz Tone [NXDN:Bit Rate=4800], 1031 Hz Tone [NXDN:Bit Rate=9600], 1011 Hz Tone [NXDN:Bit Rate=9600], Calibration (0.153 2%), 511 (0.153/PN9)

Availability:

Operating Mode:Monitor, Duplex

Menu:NXDN

Typical Completion Time:100 ms

Name:Gen Test Pattern

Tag:NXDN:Gen Test Pattern

Commands:GET, SET

Data Type:LIST

List Values: 1031 Hz Tone [NXDN:Bit Rate=4800], 1031 Hz Tone [NXDN:Bit Rate=9600], 1011 Hz Tone [NXDN:Bit Rate=9600], Calibration (0.153 2%), 511 (0.153/PN9), 511 (0.153/FSW+PN9) [Operating Mode=Generate], Interference [Operating Mode=Generate], Max Freq Deviation [Operating Mode=Generate], 1/3 Freq Deviation [Operating Mode=Generate]

Availability:

Operating Mode:Generate, Duplex


Menu:NXDN

Typical Completion Time:100 ms

Name:Modulation Mode

Tag:NXDN:Gen Mod Mode

Commands:GET, SET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 91 OF 107	

Data Type:LIST
 List Values: Off, Continuous, Burst
 Availability:
 Operating Mode:Generate
 Menu:NXDN
 Typical Completion Time:500 ms

Name:BER Test
 Tag:NXDN:BER Test
 Commands:GET, SET
 Data Type:LIST
 List Values: Stop, Start
 Availability:
 Operating Mode:Monitor
 Menu:NXDN
 Typical Completion Time:500 ms


Name:Eye Diagram Data
 Tag:NXDN:Eye Data
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor
 Menu:NXDN
 Typical Completion Time:100 ms

Name:NXDN Library Version
 Tag:NXDN:Version
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:NXDN
 Typical Completion Time:0 ms

Name:Subzone
 Tag:NXDN_TRUNK:Subzone
 Commands:GET, SET
 Data Type:LIST
 List Values: Alert/Dispatch, BER
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK
 Typical Completion Time:100 ms

Name:Modulation Mode
 Tag:NXDN_TRUNK:Gen Mod Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=BER
 Typical Completion Time:500 ms

Name:Voice Call

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 92 OF 107	

Tag:NXDN_TRUNK:Voice Call
 Commands:GET, SET
 Data Type:LIST
 List Values: Stop, Start
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms


Name:Test Pattern
 Tag:NXDN_TRUNK:Test Pattern
 Commands:GET, SET
 Data Type:LIST
 List Values: 1031 Hz Tone [NXDN_TRUNK:Bit Rate=4800], 1031 Hz Tone [NXDN_TRUNK:Bit Rate=9600], 1011 Hz Tone [NXDN_TRUNK:Bit Rate=9600], Calibration (0.153 2%), 511 (0.153/PN9)
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=BER
 Typical Completion Time:100 ms

Name:BER Test
 Tag:NXDN_TRUNK:BER Test
 Commands:GET, SET
 Data Type:LIST
 List Values: Stop, Start
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK
 Typical Completion Time:500 ms

Name:Send Status Inquiry
 Tag:NXDN_TRUNK:Status Inquiry
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:CCTx Channel
 Tag:NXDN_TRUNK:CCTx Chnl
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 1023
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:VCTx Channel
 Tag:NXDN_TRUNK:VCTx Chnl
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 1023

 Kilgore, TX	TYPE: <p style="text-align: center;">Programmer's Guide</p>	NO: <p style="text-align: center;">FCT-1110</p>	REV: <p style="text-align: center;">J</p>
	TITLE: <p style="text-align: center;">R8000 Monitor & Control</p>	PAGE: <p style="text-align: center;">93 OF 107</p>	

Availability:

Operating Mode: Duplex
 Menu: NXDN_TRUNK: Subzone=Alert/Dispatch

Typical Completion Time: 100 ms

Name: Control Chnl TX Frequency

Tag: NXDN_TRUNK: CCTx

Commands: GET, SET

Data Type: FLOAT

Range: 250000 Hz to 1000000000 Hz

Units: Hz, kHz, MHz, GHz

Availability:

Operating Mode: Duplex
 Menu: NXDN_TRUNK: Subzone=Alert/Dispatch

Typical Completion Time: 100 ms

Name: Voice Chnl TX Frequency

Tag: NXDN_TRUNK: VCTx

Commands: GET, SET

Data Type: FLOAT

Range: 250000 Hz to 1000000000 Hz

Units: Hz, kHz, MHz, GHz

Availability:

Operating Mode: Duplex
 Menu: NXDN_TRUNK: Subzone=Alert/Dispatch

Typical Completion Time: 100 ms

Name: Transmit Offset (MHz)

Tag: NXDN_TRUNK: Tx Off

Commands: GET, SET

Data Type: FLOAT

Range: 0 to 100

Availability:

Operating Mode: Duplex
 Menu: NXDN_TRUNK: Subzone=Alert/Dispatch

Typical Completion Time: 100 ms

Name: System Code

Tag: NXDN_TRUNK: SYSTEM ID

Commands: GET, SET

Data Type: STRING

char set: 0, 1, 2, 3, 4, 5, 6, 7, 8, 9

Availability:

Operating Mode: Duplex
 Menu: NXDN_TRUNK: Subzone=Alert/Dispatch

Typical Completion Time: 100 ms

Name: Site Code

Tag: NXDN_TRUNK: SITE ID


Commands: GET, SET

Data Type: STRING

char set: 0, 1, 2, 3, 4, 5, 6, 7, 8, 9

Availability:

Operating Mode: Duplex
 Menu: NXDN_TRUNK: Subzone=Alert/Dispatch

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 94 OF 107	

Typical Completion Time:100 ms

Name:Unit ID
 Tag:NXDN_TRUNK:WUID
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 65535
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms


Name:Group ID
 Tag:NXDN_TRUNK:WGID
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 65535
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:Category
 Tag:NXDN_TRUNK:Category
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 2
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:Bit Rate (bps)
 Tag:NXDN_TRUNK:Bit Rate
 Commands:GET, SET
 Data Type:LIST
 List Values: 4800, 9600
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=Alert/Dispatch, BER
 Typical Completion Time:100 ms

Name:Voice Playback
 Tag:NXDN_TRUNK:Voice Playback
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: OFF, ON
 Availability:
 Operating Mode:Duplex
 Menu:NXDN_TRUNK:Subzone=Alert/Dispatch
 Typical Completion Time:100 ms

Name:Constellation Data
 Tag:TETRA:Constellation Data
 Commands:GET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 95 OF 107	

Data Type:ARRAY
 Availability:
 Menu:TETRA
 Typical Completion Time:100 ms

Name:
 Tag:TETRA:Modulation Spectrum
 Commands:GET
 Data Type:ARRAY
 Availability:
 Menu:TETRA
 Typical Completion Time:100 ms

Name:Reset Averaging
 Tag:TETRA:Reset RX
 Commands:DO
 Data Type:FUNCTION
 Availability:
 Operating Mode:Monitor
 Menu:TETRA
 Typical Completion Time:100 ms

Name:Measurement Averaging
 Tag:TETRA:Measurement Averaging
 Commands:GET, SET
 Data Type:INTEGER
 Range: 1 to 250
 Availability:
 Operating Mode:Monitor
 Menu:TETRA
 Typical Completion Time:100 ms

Name:Unwanted Power in Slot 3
 Tag:TETRA:Unwanted Active
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: No, Yes
 Availability:
 Operating Mode:Monitor
 Menu:TETRA
 Typical Completion Time:100 ms

Name:
 Tag:TETRA:Symbol Deviation
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor
 Menu:TETRA
 Typical Completion Time:0 ms

Name:
 Tag:TETRA:EVM RMS
 Commands:GET
 Data Type:FLOAT

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 96 OF 107	

Availability:

Operating Mode:Monitor

Menu:TETRA

Typical Completion Time:0 ms

Name:

Tag:TETRA:EVM Peak

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor

Menu:TETRA

Typical Completion Time:0 ms

Name:

Tag:TETRA:Unwanted Power

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor

Menu:TETRA

Typical Completion Time:0 ms

Name:

Tag:TETRA:Residual Power

Commands:GET

Data Type:FLOAT

Availability:

Operating Mode:Monitor

Menu:TETRA

Typical Completion Time:0 ms

Name:Test Pattern

Tag:TETRA:Test Pattern

Commands:GET, SET

Data Type:LIST

List Values: 1000 Hz Tone, Silence

Availability:

Operating Mode:Generate

Menu:TETRA

Typical Completion Time:100 ms

Name:Modulation Mode

Tag:TETRA:Gen Mod Mode

Commands:GET, SET

Data Type:LIST

List Values: Off, Continuous

Availability:

Operating Mode:Generate


Menu:TETRA

Typical Completion Time:500 ms

Name:TETRA DMO Library Version

Tag:TETRA:Version

Commands:GET

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 97 OF 107	

Data Type:STRING

Availability:

Menu:TETRA

Typical Completion Time:0 ms

Name:TETRA TMO Library Version

Tag:TETRA_TMO:Version

Commands:GET

Data Type:STRING

Availability:

Menu:TETRA_TMO

Typical Completion Time:0 ms

Name:TETRA BSM Library Version

Tag:TETRA_BST:Version

Commands:GET

Data Type:STRING

Availability:

Menu:TETRA_BST

Typical Completion Time:0 ms

Name:TETRA BST1 Library Version

Tag:TETRA_BST:Version1

Commands:GET

Data Type:STRING

Availability:

Menu:TETRA_BST

Typical Completion Time:0 ms

Name:

Tag:OPTIONS:Enabled

Commands:GET

Data Type:STRING

Typical Completion Time:0 ms

Name:Synth Mode

Tag:POCSAG:Synth Mode

Commands:GET, SET

Data Type:LIST

List Values: Off, Continuous, Burst [AUDIO:Format=A/B Sequence or AUDIO:Format=5/6 Tone or AUDIO:Format=POCSAG or AUDIO:Format=General Sequence], Disconnect Tone [AUDIO:Format=DPL or AUDIO:Format=DPL Invert]

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:POCSAG

Typical Completion Time:500 ms

Name:Capcode

Tag:POCSAG:Capcode

Commands:GET, SET


Data Type:STRING

char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9

Availability:

Operating Mode:Monitor, Generate, Duplex

Menu:POCSAG

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 98 OF 107	

Typical Completion Time:100 ms


Name:Function Bits
 Tag:POCSAG:Function Bits
 Commands:GET, SET
 Data Type:LIST
 List Values: 00, 01, 10, 11
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:POCSAG
 Typical Completion Time:100 ms

Name:POCSAG Message
 Tag:POCSAG:POCSAG Message
 Commands:GET, SET
 Data Type:LIST
 List Values: Tone Only, NumericNum, NumericSet, AlphaNumUC, AlphaNumLC, AlphaNumSP, NumericCust, AlphaNumCust
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:POCSAG
 Typical Completion Time:100 ms

Name>Edit Message
 Tag:POCSAG:NumericCust Message
 Commands:GET, SET
 Data Type:STRING
 Format:(POCSAGCustom)
 char set:0, 1, 2, 3, 4, 5, 6, 7, 8, 9, U, , -,], [
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:POCSAG
 Typical Completion Time:100 ms

Name>Edit Message
 Tag:POCSAG:AlphaNumCust Message
 Commands:GET, SET
 Data Type:STRING
 Format:(POCSAGCustom)
 char set:!, ", #, \$, %, ', (,), *, +, -, ., /, 0, 1, 2, 3, 4, 5, 6, 7, 8, 9, , :; , <, =, >, ?, @, A, B, C, D, E, F, G, H, I, J, K, L, M, N, O, P, Q, R, S, T, U, V, W, X, Y, Z,], \, [, ^, _ , ` , a, b, c, d, e, f, g, h, i, j, k, l, m, n, o, p, q, r, s, t, u, v, w, x, y, z, {, , }, ~
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:POCSAG
 Typical Completion Time:100 ms

Name:Message Length
 Tag:POCSAG:Message Length
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 60
 Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 99 OF 107	

Operating Mode:Monitor, Generate, Duplex
 Menu:POCSAG
 Typical Completion Time:100 ms

Name:Data Rate
 Tag:POCSAG:Data Rate
 Commands:GET, SET
 Data Type:INTEGER
 Range: 400 to 4800
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:POCSAG
 Typical Completion Time:100 ms


Name:Polarity
 Tag:POCSAG:Polarity
 Commands:GET, SET
 Data Type:LIST
 List Values: Normal, Inverted
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:POCSAG
 Typical Completion Time:100 ms

Name>Error Bit
 Tag:POCSAG>Error Bit
 Commands:GET, SET
 Data Type:INTEGER
 Range: 0 to 2200
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:POCSAG
 Typical Completion Time:100 ms

Name:Record Results
 Tag:AUTOSCRIP:Reporting
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: Off, On
 Availability:
 Menu:AUTOSCRIP
 Typical Completion Time:500 ms

Name:
 Tag:DPMR:BER Result
 Commands:GET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Monitor
 Menu:DPMR
 Typical Completion Time:0 ms

Name:
 Tag:DPMR:Symbol Deviation

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 100 OF 107	

Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor
 Menu:DPMR
 Typical Completion Time:0 ms


Name:
 Tag:DPMR:Modulation Fidelity
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor
 Menu:DPMR
 Typical Completion Time:0 ms

Name:Test Pattern
 Tag:DPMR:Test Pattern
 Commands:GET, SET
 Data Type:LIST
 List Values: Calibration (0.153 2%), 511 (0.153/PN9), Interference [Operating Mode=Generate], Max Freq Deviation [Operating Mode=Generate], 1/3 Freq Deviation [Operating Mode=Generate]
 Availability:
 Operating Mode:Monitor, Generate
 Menu:DPMR
 Typical Completion Time:100 ms

Name:Modulation Mode
 Tag:DPMR:Gen Mod Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous, Burst
 Availability:
 Operating Mode:Generate
 Menu:DPMR
 Typical Completion Time:500 ms

Name:BER Test
 Tag:DPMR:BER Test
 Commands:GET, SET
 Data Type:LIST
 List Values: Stop, Start
 Availability:
 Operating Mode:Monitor
 Menu:DPMR
 Typical Completion Time:500 ms

Name:Ideal Sym Dev (Hz)
 Tag:DPMR:Ideal Symbol Deviation
 Commands:GET, SET
 Data Type:INTEGER
 Range: 800 to 2400
 Availability:
 Operating Mode:Monitor, Generate

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 101 OF 107	

Menu:DPMR
 Typical Completion Time:100 ms

Name:Filter
 Tag:DPMR:Filter
 Commands:GET, SET
 Data Type:LIST
 List Values: ETSI, PDR
 Availability:
 Operating Mode:Monitor, Generate
 Menu:DPMR
 Typical Completion Time:100 ms


Name:Eye Diagram Data
 Tag:DPMR:Eye Data
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor
 Menu:DPMR
 Typical Completion Time:100 ms

Name:dPMR Library Version
 Tag:DPMR:Version
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:DPMR
 Typical Completion Time:0 ms

Name:
 Tag:P25_II:BER Result
 Commands:GET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25_II
 Typical Completion Time:0 ms

Name:
 Tag:P25_II:Symbol Deviation
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25_II
 Typical Completion Time:0 ms

Name:
 Tag:P25_II:Modulation Fidelity
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 102 OF 107	

Menu:P25_II
 Typical Completion Time:0 ms


Name:Test Pattern
 Tag:P25_II:Test Pattern
 Commands:GET, SET
 Data Type:LIST
 List Values: 1031 Hz Tone, Calibration (Tone 5%), Silence, High Deviation [Operating Mode=Generate], Low Deviation [Operating Mode=Generate], Interference [Operating Mode=Generate]
 Availability:
 Operating Mode:Monitor, Generate, Duplex
 Menu:P25_II
 Typical Completion Time:100 ms

Name:Generate Modulation Type
 Tag:P25_II:Modulation Type
 Commands:GET, SET
 Data Type:LIST
 List Values: FM [Test Mode=Standard], AM [Test Mode=Standard], USB [Test Mode=Standard and Option=R8-SSB], LSB [Test Mode=Standard and Option=R8-SSB], 4FSK [Test Mode=DMR or Test Mode=DPMR or Test Mode=NXDN], GMSK~ [Test Mode=PTC-ACSES], C4FM [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], LSM [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], WCQPSK [Test Mode=PROJECT 25 or Test Mode=P25 Trunk], pi/4 DQPSK [Test Mode=PTC-ITCR or Test Mode=TETRA DMO or Test Mode=TETRA TMO or Test Mode=TETRA BST], HCPM [Test Mode=P25 II], HDQPSK [Test Mode=P25 II and Operating Mode=Monitor or Test Mode=P25 II and Operating Mode=Generate]
 Availability:
 Operating Mode:Generate
 Menu:P25_II
 Typical Completion Time:100 ms

Name:Monitor Modulation Type
 Tag:P25_II:Mon Mod Type
 Commands:GET, SET
 Data Type:LIST
 List Values: HCPM [Operating Mode=Monitor or Operating Mode=Generate], HDQPSK
 Availability:
 Operating Mode:Monitor
 Menu:P25_II
 Typical Completion Time:100 ms

Name:Modulation Mode
 Tag:P25_II:Gen Mod Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous, Burst [Operating Mode=Monitor or Operating Mode=Generate]
 Availability:
 Operating Mode:Generate, Duplex
 Menu:P25_II
 Typical Completion Time:500 ms

Name:LCH (logical channel)

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 103 OF 107	

Tag:P25_II:Gen LCH
 Commands:GET, SET
 Data Type:LIST
 List Values: 0, 1
 Availability:
 Operating Mode:Generate, Duplex
 Menu:P25_II
 Typical Completion Time:100 ms


Name:BER Test
 Tag:P25_II:BER Test
 Commands:GET, SET
 Data Type:LIST
 List Values: Stop, Start
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25_II
 Typical Completion Time:500 ms

Name:Eye Diagram Data
 Tag:P25_II:Eye Data
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:P25_II
 Typical Completion Time:100 ms

Name:P25 Phase 2 Library Version
 Tag:P25_II:Version
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:P25_II
 Typical Completion Time:0 ms

Name:Mon Symbol Rate (sps)
 Tag:PTC_ITCR:Mon Sym Rate
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: 8000, 16000
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:100 ms

Name:Gen Symbol Rate (sps)
 Tag:PTC_ITCR:Gen Sym Rate
 Commands:GET, SET
 Data Type:BOOLEAN
 List Values: 8000, 16000
 Availability:
 Operating Mode:Generate, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:100 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 104 OF 107	

Name:BER Test
 Tag:PTC_ITCR:BER Test
 Commands:GET, SET
 Data Type:LIST
 List Values: Stop, Start
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:500 ms


Name:Modulation Mode
 Tag:PTC_ITCR:Gen Mod Mode
 Commands:GET, SET
 Data Type:LIST
 List Values: Off, Continuous
 Availability:
 Operating Mode:Generate, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:500 ms

Name:Packet Sync Status
 Tag:PTC_ITCR:Sync
 Commands:GET
 Data Type:BOOLEAN
 List Values:
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:
 Tag:PTC_ITCR:BER Result
 Commands:GET
 Data Type:FLOAT
 Range: 0 to 100
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:Average Power (dBm)
 Tag:PTC_ITCR:Average Power
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:Peak Power (dBm)
 Tag:PTC_ITCR:Peak Power
 Commands:GET
 Data Type:FLOAT
 Availability:

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 105 OF 107	

Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:
 Tag:PTC_ITCR:EVM
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms


Name:
 Tag:PTC_ITCR:IQ Imbalance
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:
 Tag:PTC_ITCR:Phase Err
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:
 Tag:PTC_ITCR:Mag Err
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:
 Tag:PTC_ITCR:PAR
 Commands:GET
 Data Type:FLOAT
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:
 Tag:PTC_ITCR:Packet Count
 Commands:GET
 Data Type:INTEGER
 Availability:
 Operating Mode:Monitor, Duplex

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 106 OF 107	

Menu:PTC_ITCR
 Typical Completion Time:0 ms


Name:
 Tag:PTC_ITCR:Header Resync Count
 Commands:GET
 Data Type:INTEGER
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:
 Tag:PTC_ITCR>Last Packet Index
 Commands:GET
 Data Type:INTEGER
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:Eye Diagram Data
 Tag:PTC_ITCR:Eye Data
 Commands:GET
 Data Type:ARRAY
 Availability:
 Operating Mode:Monitor, Duplex
 Menu:PTC_ITCR
 Typical Completion Time:100 ms

Name:PTC-ITCR Library Version
 Tag:PTC_ITCR:Version
 Commands:GET
 Data Type:STRING
 Availability:
 Menu:PTC_ITCR
 Typical Completion Time:0 ms

Name:
 Tag:UTILITY>LastParameter
 Commands:GET
 Data Type:INTEGER
 Availability:
 Option:R8-OEM
 Menu:UTILITY
 Typical Completion Time:0 ms

 Kilgore, TX	TYPE: Programmer's Guide	NO: FCT-1110	REV: J
	TITLE: R8000 Monitor & Control	PAGE: 107 OF 107	

J – Updates for 3.4.2	D. Bulgrien	DC	10/30/18	0211
H – Updates for 3.3	D. Bulgrien	DC	6/27/18	0198
G – Updates for 3.1	D. Bulgrien	DC	3/7/18	0167
F – Updates for 3.0.0.0	M.Mullin	DC	11/10/17	0156
E – Updates for 2.3.4.0	D. Bulgrien	DC	5/18/17	0118
D – Updates for 2.2.0.0	D. Bulgrien	DC	1/15/17	0098
C – Updates for 2.1.0.0	M. Mullins	F.Fu	8/18/16	0063
B – Updates for 2.0.0.0	D. Bulgrien	F. Fu	8/17/16	0052
A – Was CG1110; 1.19 updates	M. Mullins	F.Fu	11/5/15	0007
Revision – Change	Requested By	Released By	Date	ECO#